

CODE BOOK

For Frequency Program

76,9875 - 88,9875

160,1875 - 172,1875

Listan gäller för bla Kraco Pro-20

(apparater som programmeras med ettor & nollor)



31	76.9875	1	1	1	1	0	0	0	0	0	0
32	77.000	0	0	0	0	0	1	0	0	0	0
33	.0125	1	0	0	0	0	1	0	0	0	0
34	.025	0	1	0	0	0	1	0	0	0	0
35	.0375	1	1	0	0	0	1	0	0	0	0
36	.050	0	0	1	0	0	1	0	0	0	0
37	.0625	1	0	1	0	0	1	0	0	0	0
38	.075	0	1	1	0	0	1	0	0	0	0
39	.0875	1	1	1	0	0	1	0	0	0	0
40	77.100	0	0	0	1	0	1	0	0	0	0
41	.1125	1	0	0	1	0	1	0	0	0	0
42	.125	0	1	0	1	0	1	0	0	0	0
43	.1375	1	1	0	1	0	1	0	0	0	0
44	.150	0	0	1	1	0	1	0	0	0	0
45	.1625	1	0	1	1	0	1	0	0	0	0
46	.175	0	1	1	1	0	1	0	0	0	0
47	.1875	1	1	1	1	0	1	0	0	0	0
48	77.200	0	0	0	0	1	1	0	0	0	0
49	.2125	1	0	0	0	1	1	0	0	0	0
50	.225	0	1	0	0	1	1	0	0	0	0
51	.2375	1	1	0	0	1	1	0	0	0	0
52	.250	0	0	1	0	1	1	0	0	0	0
53	.2625	1	0	1	0	1	1	0	0	0	0
54	.275	0	1	1	0	1	1	0	0	0	0
55	.2875	1	1	1	0	1	1	0	0	0	0
56	77.300	0	0	0	1	1	1	0	0	0	0
57	.3125	1	0	0	1	1	1	0	0	0	0
58	.325	0	1	0	1	1	1	0	0	0	0
59	.3375	1	1	0	1	1	1	0	0	0	0
60	.350	0	0	1	1	1	1	0	0	0	0
61	.3625	1	0	1	1	1	1	0	0	0	0
62	.5	0	1	1	1	1	1	0	0	0	0
LL 63	.3875	1	1	1	1	1	1	0	0	0	0

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H.L. N11	NOTE
LL 64		77.400	0	0	0	0	0	0	1	0	0	0	0	
65		.4125	1	0	0	0	0	0	1	0	0	0	0	
66		.425	0	1	0	0	0	0	1	0	0	0	0	
67		.4375	1	1	0	0	0	0	1	0	0	0	0	
68		.450	0	0	1	0	0	0	1	0	0	0	0	
69		.4625	1	0	1	0	0	0	1	0	0	0	0	
70		.475	0	1	1	0	0	0	1	0	0	0	0	
71		.4875	1	1	1	0	0	0	1	0	0	0	0	
72		77.500	0	0	0	1	0	0	1	0	0	0	0	
73		.5125	1	0	0	1	0	0	1	0	0	0	0	
74		.525	0	1	0	1	0	0	1	0	0	0	0	
75		.5375	1	1	0	1	0	0	1	0	0	0	0	
76		.550	0	0	1	1	0	0	1	0	0	0	0	
77		.5625	1	0	1	1	0	0	1	0	0	0	0	
78		.575	0	1	1	1	0	0	1	0	0	0	0	
79		.5875	1	1	1	1	0	0	1	0	0	0	0	
80		77.600	0	0	0	0	1	0	1	0	0	0	0	
81		.6125	1	0	0	0	1	0	1	0	0	0	0	
82		.625	0	1	0	0	1	0	1	0	0	0	0	
83		.6375	1	1	0	0	1	0	1	0	0	0	0	
84		.650	0	0	1	0	1	0	1	0	0	0	0	
85		.6625	1	0	1	0	1	0	1	0	0	0	0	
86		.675	0	1	1	0	1	0	1	0	0	0	0	
87		.6875	1	1	1	0	1	0	1	0	0	0	0	
88		77.700	0	0	0	1	1	0	1	0	0	0	0	
89		.7125	1	0	0	1	1	0	1	0	0	0	0	
90		.725	0	1	0	1	1	0	1	0	0	0	0	
91		.7375	1	1	0	1	1	0	1	0	0	0	0	
92		.750	0	0	1	1	1	0	1	0	0	0	0	
93		.7625	1	0	1	1	1	0	1	0	0	0	0	
94		.775	0	1	1	1	1	0	1	0	0	0	0	
95		.7875	1	1	1	1	1	0	1	0	0	0	0	
96		77.800	0	0	0	0	0	1	1	0	0	0	0	
97		.8125	1	0	0	0	0	1	1	0	0	0	0	
98		.825	0	1	0	0	0	1	1	0	0	0	0	
99		.8375	1	1	0	0	0	1	1	0	0	0	0	
100		.850	0	0	1	0	0	1	1	0	0	0	0	
101		.8625	1	0	1	0	0	1	1	0	0	0	0	
102		.875	0	1	1	0	0	1	1	0	0	0	0	
103		.8875	1	1	1	0	0	1	1	0	0	0	0	
104		77.900	0	0	0	1	0	1	1	0	0	0	0	
105		.9125	1	0	0	1	0	1	1	0	0	0	0	
106		.925	0	1	0	1	0	1	1	0	0	0	0	
107		.9375	1	1	0	1	0	1	1	0	0	0	0	
108		.950	0	0	1	1	0	1	1	0	0	0	0	
109		.9625	1	0	1	1	0	1	1	0	0	0	0	
110		.975	0	1	1	1	0	1	1	0	0	0	0	
111		.9875	1	1	1	1	0	1	1	0	0	0	0	
112		78.000	0	0	0	0	1	1	1	0	0	0	0	
113		.0125	1	0	0	0	1	1	1	0	0	0	0	
114		.025	0	1	0	0	1	1	1	0	0	0	0	
115		.0375	1	1	0	0	1	1	1	0	0	0	0	
116		.050	0	0	1	0	1	1	1	0	0	0	0	
117		.0525	1	0	1	0	1	1	1	0	0	0	0	
118		.075	0	1	1	0	1	1	1	0	0	0	0	
119		.0875	1	1	1	0	1	1	1	0	0	0	0	
120		78.100	0	0	0	1	1	1	1	0	0	0	0	
121		.1125	1	0	0	1	1	1	1	0	0	0	0	
122		.125	0	1	0	1	1	1	1	0	0	0	0	
123		.1375	1	1	0	1	1	1	1	0	0	0	0	
124		.150	0	0	1	1	1	1	1	0	0	0	0	
125		.1625	1	0	1	1	1	1	1	0	0	0	0	
126		.175	0	1	1		1	1	1	0		0	0	
LL 127		.1875	1	1	1	1	1	1	1	0		0	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
LL 128		78. 200	0	0	0	0	0	0	0	1	0	0	0	
129		. 2125	1	0	0	0	0	0	0	1	0	0	0	
130		. 225	0	1	0	0	0	0	0	1	0	0	0	
131		. 2375	1	1	0	0	0	0	0	1	0	0	0	
132		. 250	0	0	1	0	0	0	0	1	0	0	0	
133		. 2625	1	0	1	0	0	0	0	1	0	0	0	
134		. 275	0	1	1	0	0	0	0	1	0	0	0	
135		. 2875	1	1	1	0	0	0	0	1	0	0	0	
136		78. 300	0	0	0	1	0	0	0	1	0	0	0	
137		. 3125	1	0	0	1	0	0	0	1	0	0	0	
138		. 325	0	1	0	1	0	0	0	1	0	0	0	
139		. 3375	1	1	0	1	0	0	0	1	0	0	0	
140		. 350	0	0	1	1	0	0	0	1	0	0	0	
141		. 3625	1	0	1	1	0	0	0	1	0	0	0	
142		. 375	0	1	1	0	0	0	0	1	0	0	0	
143		. 3875	1	1	1	1	0	0	0	1	0	0	0	
144		78. 400	0	0	0	0	1	0	0	1	0	0	0	
145		. 4125	1	0	0	0	1	0	0	1	0	0	0	
146		. 425	0	1	0	0	1	0	0	1	0	0	0	
147		. 4375	1	1	0	0	1	0	0	1	0	0	0	
148		. 450	0	0	1	0	1	0	0	1	0	0	0	
149		. 4625	1	0	1	0	1	0	0	1	0	0	0	
150		. 475	0	1	1	0	1	0	0	1	0	0	0	
151		. 4875	1	1	1	0	1	0	0	1	0	0	0	
152		78. 500	0	0	0	1	1	0	0	1	0	0	0	
153		. 5125	1	0	0	1	1	0	0	1	0	0	0	
154		. 525	0	1	0	1	1	0	0	1	0	0	0	
155		. 5375	1	1	0	1	1	0	0	1	0	0	0	
156		. 550	0	0	1	1	1	0	0	1	0	0	0	
157		. 5625	1	0	1	1	1	0	0	1	0	0	0	
158		. 575	0	1	1	1	1	0	0	1	0	0	0	
159		. 5875	1	1	1	1	1	0	0	1	0	0	0	
160		78. 600	0	0	0	0	0	1	0	1	0	0	0	
161		. 6125	1	0	0	0	0	1	0	1	0	0	0	
162		. 625	0	1	0	0	0	1	0	1	0	0	0	
163		. 6375	1	1	0	0	0	1	0	1	0	0	0	
164		. 650	0	0	1	0	0	1	0	1	0	0	0	
165		. 6625	1	0	1	0	0	1	0	1	0	0	0	
166		. 675	0	1	1	0	0	1	0	1	0	0	0	
167		. 6875	1	1	1	0	0	1	0	1	0	0	0	
168		78. 700	0	0	0	1	0	1	0	1	0	0	0	
169		. 7125	1	0	0	1	0	1	0	1	0	0	0	
170		. 725	0	1	0	1	0	1	0	1	0	0	0	
171		. 7375	1	1	0	1	0	1	0	1	0	0	0	
172		. 750	0	0	1	1	0	1	0	1	0	0	0	
173		. 7625	1	0	1	1	0	1	0	1	0	0	0	
174		. 775	0	1	1	1	0	1	0	1	0	0	0	
175		. 7875	1	1	1	1	0	1	0	1	0	0	0	
176		78. 800	0	0	0	0	1	1	0	1	0	0	0	
177		. 8125	1	0	0	0	1	1	0	1	0	0	0	
178		. 825	0	1	0	0	1	1	0	1	0	0	0	
179		. 8375	1	1	0	0	1	1	0	1	0	0	0	
180		. 850	0	0	1	0	1	1	0	1	0	0	0	
181		. 8625	1	0	1	0	1	1	0	1	0	0	0	
182		. 875	0	1	1	0	1	1	0	1	0	0	0	
183		. 8875	1	1	1	0	1	1	0	1	0	0	0	
184		78. 900	0	0	0	1	1	1	0	1	0	0	0	
185		. 9125	1	0	0	1	1	1	0	1	0	0	0	
186		. 925	0	1	0	1	1	1	0	1	0	0	0	
187		. 9375	1	1	0	1	1	1	0	1	0	0	0	
188		. 950	0	0	1	1	1	1	0	1	0	0	0	
189		. 9625	1	0	1	1	1	1	0	1	0	0	0	
190		. 975	0	1	1	1	1	1	0	1	0	0	0	
LL 191		. 9875	1	1	1	1	1	1	0	1	0	0	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
LL 192		79.000	0	0	0	0	0	0	1	1	0	0	0	
193		.0125	1	0	0	0	0	0	1	1	0	0	0	
194		.025	0	1	0	0	0	0	1	1	0	0	0	
195		.0375	1	1	0	0	0	0	1	1	0	0	0	
196		.050	0	0	1	0	0	0	1	1	0	0	0	
197		.0625	1	0	1	0	0	0	1	1	0	0	0	
198		.075	0	1	1	0	0	0	1	1	0	0	0	
199		.0875	1	1	1	0	0	0	1	1	0	0	0	
200		79.100	0	0	0	1	0	0	1	1	0	0	0	
201		.1125	1	0	0	1	0	0	1	1	0	0	0	
202		.125	0	1	0	1	0	0	1	1	0	0	0	
203		.1375	1	1	0	1	0	0	1	1	0	0	0	
204		.150	0	0	1	1	0	0	1	1	0	0	0	
205		.1625	1	0	1	1	0	0	1	1	0	0	0	
206		.175	0	1	1	1	0	0	1	1	0	0	0	
207		.1875	1	1	1	1	0	0	1	1	0	0	0	
208		79.200	0	0	0	0	1	0	1	1	0	0	0	
209		.2125	1	0	0	0	1	0	1	1	0	0	0	
210		.225	0	1	0	0	1	0	1	1	0	0	0	
211		.2375	1	1	0	0	1	0	1	1	0	0	0	
212		.250	0	0	1	0	1	0	1	1	0	0	0	
213		.2625	1	0	1	0	1	0	1	1	0	0	0	
214		.275	0	1	1	0	1	0	1	1	0	0	0	
215		.2875	1	1	1	0	1	0	1	1	0	0	0	
216		79.300	0	0	0	1	1	0	1	1	0	0	0	
217		.3125	1	0	0	1	1	0	1	1	0	0	0	
218		.325	0	1	0	1	1	0	1	1	0	0	0	
219		.3375	1	1	0	1	1	0	1	1	0	0	0	
220		.350	0	0	1	1	1	0	1	1	0	0	0	
221		.3625	1	0	1	1	1	0	1	1	0	0	0	
222		.375	0	1	1	1	1	0	1	1	0	0	0	
223		.3875	1	1	1	1	1	0	1	1	0	0	0	
224		79.400	0	0	0	0	0	1	1	1	0	0	0	
225		.4125	1	0	0	0	0	1	1	1	0	0	0	
226		.425	0	1	0	0	0	1	1	1	0	0	0	
227		.4375	1	1	0	0	0	1	1	1	0	0	0	
228		.450	0	0	1	0	0	1	1	1	0	0	0	
229		.4625	1	0	1	0	0	1	1	1	0	0	0	
230		.475	0	1	1	0	0	1	1	1	0	0	0	
231		.4875	1	1	1	0	0	1	1	1	0	0	0	
232		79.500	0	0	0	1	0	1	1	1	0	0	0	
233		.5125	1	0	0	1	0	1	1	1	0	0	0	
234		.525	0	1	0	1	0	1	1	1	0	0	0	
235		.5375	1	1	0	1	0	1	1	1	0	0	0	
236		.550	0	0	1	1	0	1	1	1	0	0	0	
237		.5625	1	0	1	1	0	1	1	1	0	0	0	
238		.575	0	1	1	1	0	1	1	1	0	0	0	
239		.5875	1	1	1	1	0	1	1	1	0	0	0	
240		79.600	0	0	0	0	1	1	1	1	0	0	0	
241		.6125	1	0	0	0	1	1	1	1	0	0	0	
242		.625	0	1	0	0	1	1	1	1	0	0	0	
243		.6375	1	1	0	0	1	1	1	1	0	0	0	
244		.650	0	0	1	0	1	1	1	1	0	0	0	
245		.6625	1	0	1	0	1	1	1	1	0	0	0	
246		.675	0	1	1	0	1	1	1	1	0	0	0	
247		.6875	1	1	1	0	1	1	1	1	0	0	0	
248		79.700	0	0	0	1	1	1	1	1	0	0	0	
249		.7125	1	0	0	1	1	1	1	1	0	0	0	
250		.725	0	1	0	1	1	1	1	1	0	0	0	
251		.7375	1	1	0	1	1	1	1	1	0	0	0	
252		.750	0	0	1	1	1	1	1	1	0	0	0	
253		.7625	1	0	1	1	1	1	1	1	0	0	0	
254		.775	0	1	1	1	1	1	1	1	0	0	0	
LL 255		.7875	1	1	1	1	1	1	1	1	0	0	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
LL 256		79. 800	0	0	0	0	0	0	0	0	1	0	0	
257		. 8125	1	0	0	0	0	0	0	0	1	0	0	
258		. 825	0	1	0	0	0	0	0	0	1	0	0	
259		. 8375	1	1	0	0	0	0	0	0	1	0	0	
260		. 850	0	0	1	0	0	0	0	0	1	0	0	
261		. 8625	1	0	1	0	0	0	0	0	1	0	0	
262		. 875	0	1	1	0	0	0	0	0	1	0	0	
263		. 8875	1	1	1	0	0	0	0	0	1	0	0	
264		79. 900	0	0	0	1	0	0	0	0	1	0	0	
265		. 9125	1	0	0	1	0	0	0	0	1	0	0	
266		. 925	0	1	0	1	0	0	0	0	1	0	0	
267		. 9375	1	1	0	1	0	0	0	0	1	0	0	
268		. 950	0	0	1	1	0	0	0	0	1	0	0	
269		. 9625	1	0	1	1	0	0	0	0	1	0	0	
270		. 975	0	1	1	1	0	0	0	0	1	0	0	
271		. 9875	1	1	1	1	0	0	0	0	1	0	0	
272		80. 000	0	0	0	0	1	0	0	0	1	0	0	
273		. 0125	1	0	0	0	1	0	0	0	1	0	0	
274		. 025	0	1	0	0	1	0	0	0	1	0	0	
275		. 0375	1	1	0	0	1	0	0	0	1	0	0	
276		. 050	0	0	1	0	1	0	0	0	1	0	0	
277		. 0625	1	0	1	0	1	0	0	0	1	0	0	
278		. 075	0	1	1	0	1	0	0	0	1	0	0	
279		. 0875	1	1	1	0	1	0	0	0	1	0	0	
280		80. 100	0	0	0	1	1	0	0	0	1	0	0	
281		. 1125	1	0	0	1	1	0	0	0	1	0	0	
282		. 125	0	1	0	1	1	0	0	0	1	0	0	
283		. 1375	1	1	0	1	1	0	0	0	1	0	0	
284		. 150	0	0	1	1	1	0	0	0	1	0	0	
285		. 1625	1	0	1	1	1	0	0	0	1	0	0	
286		. 175	0	1	1	1	1	0	0	0	1	0	0	
287		. 1875	1	1	1	1	1	0	0	0	1	0	0	
288		80. 200	0	0	0	0	0	1	0	0	1	0	0	
289		. 2125	1	0	0	0	0	1	0	0	1	0	0	
290		. 225	0	1	0	0	0	1	0	0	1	0	0	
291		. 2375	1	1	0	0	0	1	0	0	1	0	0	
292		. 250	0	0	1	0	0	1	0	0	1	0	0	
293		. 2625	1	0	1	0	0	1	0	0	1	0	0	
294		. 275	0	1	1	0	0	1	0	0	1	0	0	
295		. 2875	1	1	1	0	0	1	0	0	1	0	0	
296		80. 300	0	0	0	1	0	1	0	0	1	0	0	
297		. 3125	1	0	0	1	0	1	0	0	1	0	0	
298		. 325	0	1	0	1	0	1	0	0	1	0	0	
299		. 3375	1	1	0	1	0	1	0	0	1	0	0	
300		. 350	0	0	1	1	0	1	0	0	1	0	0	
301		. 3625	1	0	1	1	0	1	0	0	1	0	0	
302		. 375	0	1	1	1	0	1	0	0	1	0	0	
303		. 3875	1	1	1	1	0	1	0	0	1	0	0	
304		80. 400	0	0	0	0	1	1	0	0	1	0	0	
305		. 4125	1	0	0	0	1	1	0	0	1	0	0	
306		. 425	0	1	0	0	1	1	0	0	1	0	0	
307		. 4375	1	1	0	0	1	1	0	0	1	0	0	
308		. 450	0	0	1	0	1	1	0	0	1	0	0	
309		. 4625	1	0	1	0	1	1	0	0	1	0	0	
310		. 475	0	1	1	0	1	1	0	0	1	0	0	
311		. 4875	1	1	1	0	1	1	0	0	1	0	0	
312		80. 500	0	0	0	1	1	1	0	0	1	0	0	
313		. 5125	1	0	0	1	1	1	0	0	1	0	0	
314		. 525	0	1	0	1	1	1	0	0	1	0	0	
315		. 5375	1	1	0	1	1	1	0	0	1	0	0	
316		. 550	0	0	1	1	1	1	0	0	1	0	0	
317		. 5625	1	0	1	1	1	1	0	0	1	0	0	
318		. 575	0	1	1	1	1	1	0	0	1	0	0	
LL 319		. 5875	1	1	1	1	1	1	0	0	1	0	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H.L N11	NOTE
LL 320		80.600	0	0	0	0	0	0	1	0	1	0	0	
321		.6125	1	0	0	0	0	0	1	0	1	0	0	
322		.625	0	1	0	0	0	0	1	0	1	0	0	
323		.6375	1	1	0	0	0	0	1	0	1	0	0	
324		.650	0	0	1	0	0	0	1	0	1	0	0	
325		.6625	1	0	1	0	0	0	1	0	1	0	0	
326		.675	0	1	1	0	0	0	1	0	1	0	0	
327		.6875	1	1	1	0	0	0	1	0	1	0	0	
328		80.700	0	0	0	1	0	0	1	0	1	0	0	
329		.7125	1	0	0	1	0	0	1	0	1	0	0	
330		.725	0	1	0	1	0	0	1	0	1	0	0	
331		.7375	1	1	0	1	0	0	1	0	1	0	0	
332		.750	0	0	1	1	0	0	1	0	1	0	0	
333		.7625	1	0	1	1	0	0	1	0	1	0	0	
334		.775	0	1	1	1	0	0	1	0	1	0	0	
335		.7875	1	1	1	1	0	0	1	0	1	0	0	
336		80.800	0	0	0	0	1	0	1	0	1	0	0	
337		.8125	1	0	0	0	1	0	1	0	1	0	0	
338		.825	0	1	0	0	1	0	1	0	1	0	0	
339		.8375	1	1	0	0	1	0	1	0	1	0	0	
340		.850	0	0	1	0	1	0	1	0	1	0	0	
341		.8625	1	0	1	0	1	0	1	0	1	0	0	
342		.875	0	1	1	0	1	0	1	0	1	0	0	
343		.8875	1	1	1	0	1	0	1	0	1	0	0	
344		80.900	0	0	0	1	1	0	1	0	1	0	0	
345		.9125	1	0	0	1	1	0	1	0	1	0	0	
346		.925	0	1	0	1	1	0	1	0	1	0	0	
347		.9375	1	1	0	1	1	0	1	0	1	0	0	
348		.950	0	0	1	1	1	0	1	0	1	0	0	
349		.9625	1	0	1	1	1	0	1	0	1	0	0	
350		.975	0	1	1	1	1	0	1	0	1	0	0	
351		.9875	1	1	1	1	1	0	1	0	1	0	0	
352		81.000	0	0	0	0	0	1	1	0	1	0	0	
353		.0125	1	0	0	0	0	1	1	0	1	0	0	
354		.025	0	1	0	0	0	1	1	0	1	0	0	
355		.0375	1	1	0	0	0	1	1	0	1	0	0	
356		.050	0	0	1	0	0	1	1	0	1	0	0	
357		.0625	1	0	1	0	0	1	1	0	1	0	0	
358		.075	0	1	1	0	0	1	1	0	1	0	0	
359		.0875	1	1	1	0	0	1	1	0	1	0	0	
360		81.100	0	0	0	1	0	1	1	0	1	0	0	
361		.1125	1	0	0	1	0	1	1	0	1	0	0	
362		.125	0	1	0	1	0	1	1	0	1	0	0	
363		.1375	1	1	0	1	0	1	1	0	1	0	0	
364		.150	0	0	1	1	0	1	1	0	1	0	0	
365		.1625	1	0	1	1	0	1	1	0	1	0	0	
366		.175	0	1	1	1	0	1	1	0	1	0	0	
367		.1875	1	1	1	1	0	1	1	0	1	0	0	
368		81.200	0	0	0	0	1	1	1	0	1	0	0	
369		.2125	1	0	0	0	1	1	1	0	1	0	0	
370		.225	0	1	0	0	1	1	1	0	1	0	0	
371		.2375	1	1	0	0	1	1	1	0	1	0	0	
372		.250	0	0	1	0	1	1	1	0	1	0	0	
373		.2625	1	0	1	0	1	1	1	0	1	0	0	
374		.275	0	1	1	0	1	1	1	0	1	0	0	
375		.2875	1	1	1	0	1	1	1	0	1	0	0	
376		81.300	0	0	0	1	1	1	1	0	1	0	0	
377		.3125	1	0	0	1	1	1	1	0	1	0	0	
378		.325	0	1	0	1	1	1	1	0	1	0	0	
379		.3375	1	1	0	1	1	1	1	0	1	0	0	
380		.350	0	0	1	1	1	1	1	0	1	0	0	
381		.3625	1	0	1	1	1	1	1	0	1	0	0	
382		.375	0	1	1	1	1	1	1	0	1	0	0	
LL 383		.3875	1	1	1	1	1	1	1	0	1	0	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
LL 384		81.400	0	0	0	0	0	0	0	1	1	0	0	
385		.4125	1	0	0	0	0	0	0	1	1	0	0	
386		.425	0	1	0	0	0	0	0	1	1	0	0	
387		.4375	1	1	0	0	0	0	0	1	1	0	0	
388		.450	0	0	1	0	0	0	0	1	1	0	0	
389		.4625	1	0	1	0	0	0	0	1	1	0	0	
390		.475	0	1	1	0	0	0	0	1	1	0	0	
391		.4875	1	1	1	0	0	0	0	1	1	0	0	
392		81.500	0	0	0	1	0	0	0	1	1	0	0	
393		.5125	1	0	0	1	0	0	0	1	1	0	0	
394		.525	0	1	0	1	0	0	0	1	1	0	0	
395		.5375	1	1	0	1	0	0	0	1	1	0	0	
396		.550	0	0	1	1	0	0	0	1	1	0	0	
397		.5625	1	0	1	1	0	0	0	1	1	0	0	
398		.575	0	1	1	1	0	0	0	1	1	0	0	
399		.5875	1	1	1	1	0	0	0	1	1	0	0	
400		81.600	0	0	0	0	1	0	0	1	1	0	0	
401		.6125	1	0	0	0	1	0	0	1	1	0	0	
402		.625	0	1	0	0	1	0	0	1	1	0	0	
403		.6375	1	1	0	0	1	0	0	1	1	0	0	
404		.650	0	0	1	0	1	0	0	1	1	0	0	
405		.6625	1	0	1	0	1	0	0	1	1	0	0	
406		.675	0	1	1	0	1	0	0	1	1	0	0	
407		.6875	1	1	1	0	1	0	0	1	1	0	0	
408		81.700	0	0	0	1	1	0	0	1	1	0	0	
409		.7125	1	0	0	1	1	0	0	1	1	0	0	
410		.725	0	1	0	1	1	0	0	1	1	0	0	
411		.7375	1	1	0	1	1	0	0	1	1	0	0	
412		.750	0	0	1	1	1	0	0	1	1	0	0	
413		.7625	1	0	1	1	1	0	0	1	1	0	0	
414		.775	0	1	1	1	1	0	0	1	1	0	0	
415		.7875	1	1	1	1	1	0	0	1	1	0	0	
416		81.800	0	0	0	0	0	1	0	1	1	0	0	
417		.8125	1	0	0	0	0	1	0	1	1	0	0	
418		.825	0	1	0	0	0	1	0	1	1	0	0	
419		.8375	1	1	0	0	0	1	0	1	1	0	0	
420		.850	0	0	1	0	0	1	0	1	1	0	0	
421		.8625	1	0	1	0	0	1	0	1	1	0	0	
422		.875	0	1	1	0	0	1	0	1	1	0	0	
423		.8875	1	1	1	0	0	1	0	1	1	0	0	
424		81.900	0	0	0	1	0	1	0	1	1	0	0	
425		.9125	1	0	0	1	0	1	0	1	1	0	0	
426		.925	0	1	0	1	0	1	0	1	1	0	0	
427		.9375	1	1	0	1	0	1	0	1	1	0	0	
428		.950	0	0	1	1	0	1	0	1	1	0	0	
429		.9625	1	0	1	1	0	1	0	1	1	0	0	
430		.975	0	1	1	1	0	1	0	1	1	0	0	
431		.9875	1	1	1	1	0	1	0	1	1	0	0	
432		82.000	0	0	0	0	1	1	0	1	1	0	0	
433		.0125	1	0	0	0	1	1	0	1	1	0	0	
434		.025	0	1	0	0	1	1	0	1	1	0	0	
435		.0375	1	1	0	0	1	1	0	1	1	0	0	
436		.050	0	0	1	0	1	1	0	1	1	0	0	
437		.0625	1	0	1	0	1	1	0	1	1	0	0	
438		.075	0	1	1	0	1	1	0	1	1	0	0	
439		.0875	1	1	1	0	1	1	0	1	1	0	0	
440		82.100	0	0	0	1	1	1	0	1	1	0	0	
441		.1125	1	0	0	1	1	1	0	1	1	0	0	
442		.125	0	1	0	1	1	1	0	1	1	0	0	
443		.1375	1	1	0	1	1	1	0	1	1	0	0	
444		.150	0	0	1	1	1	1	0	1	1	0	0	
445		.1625	1	0	1	1	1	1	0	1	1	0	0	
446		.175	0	1	1	1	1	1	0	1	1	0	0	
LL 447		.1875	1	1	1	1	1	1	0	1	1	0	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H. L. N11	NOTE
LL 448		82.200	0	0	0	0	0	0	1	1	1	0	0	
449		.2125	1	0	0	0	0	0	1	1	1	0	0	
450		.225	0	1	0	0	0	0	1	1	1	0	0	
451		.2375	1	1	0	0	0	0	1	1	1	0	0	
452		.250	0	0	1	0	0	0	1	1	1	0	0	
453		.2625	1	0	1	0	0	0	1	1	1	0	0	
454		.275	0	1	1	0	0	0	1	1	1	0	0	
455		.2875	1	1	1	0	0	0	1	1	1	0	0	
456		82.300	0	0	0	1	0	0	1	1	1	0	0	
457		.3125	1	0	0	1	0	0	1	1	1	0	0	
458		.325	0	1	0	1	0	0	1	1	1	0	0	
459		.3375	1	1	0	1	0	0	1	1	1	0	0	
460		.350	0	0	1	1	0	0	1	1	1	0	0	
461		.3625	1	0	1	1	0	0	1	1	1	0	0	
462		.375	0	1	1	1	0	0	1	1	1	0	0	
463		.3875	1	1	1	1	0	0	1	1	1	0	0	
464		82.400	0	0	0	0	1	0	1	1	1	0	0	
465		.4125	1	0	0	0	1	0	1	1	1	0	0	
466		.425	0	1	0	0	1	0	1	1	1	0	0	
467		.4375	1	1	0	0	1	0	1	1	1	0	0	
468		.450	0	0	1	0	1	0	1	1	1	0	0	
469		.4625	1	0	1	0	1	0	1	1	1	0	0	
470		.475	0	1	1	0	1	0	1	1	1	0	0	
471		.4875	1	1	1	0	1	0	1	1	1	0	0	
472		82.500	0	0	0	1	1	0	1	1	1	0	0	
473		.5125	1	0	0	1	1	0	1	1	1	0	0	
474		.525	0	1	0	1	1	0	1	1	1	0	0	
475		.5375	1	1	0	1	1	0	1	1	1	0	0	
476		.550	0	0	1	1	1	0	1	1	1	0	0	
477		.5625	1	0	1	1	1	0	1	1	1	0	0	
478		.575	0	1	1	1	1	0	1	1	1	0	0	
479		.5875	1	1	1	1	1	0	1	1	1	0	0	
480		82.600	0	0	0	0	0	1	1	1	1	0	0	
481		.6125	1	0	0	0	0	1	1	1	1	0	0	
482		.625	0	1	0	0	0	1	1	1	1	0	0	
483		.6375	1	1	0	0	0	1	1	1	1	0	0	
484		.650	0	0	1	0	0	1	1	1	1	0	0	
485		.6625	1	0	1	0	0	1	1	1	1	0	0	
486		.675	0	1	1	0	0	1	1	1	1	0	0	
487		.6875	1	1	1	0	0	1	1	1	1	0	0	
488		82.700	0	0	0	1	0	1	1	1	1	0	0	
489		.7125	1	0	0	1	0	1	1	1	1	0	0	
490		.725	0	1	0	1	0	1	1	1	1	0	0	
491		.7375	1	1	0	1	0	1	1	1	1	0	0	
492		.750	0	0	1	1	0	1	1	1	1	0	0	
493		.7625	1	0	1	1	0	1	1	1	1	0	0	
494		.775	0	1	1	1	0	1	1	1	1	0	0	
495		.7875	1	1	1	1	0	1	1	1	1	0	0	
496		82.800	0	0	0	0	1	1	1	1	1	0	0	
497		.8125	1	0	0	0	1	1	1	1	1	0	0	
498		.825	0	1	0	0	1	1	1	1	1	0	0	
499		.8375	1	1	0	0	1	1	1	1	1	0	0	
500		.850	0	0	1	0	1	1	1	1	1	0	0	
501		.8625	1	0	1	0	1	1	1	1	1	0	0	
502		.875	0	1	1	0	1	1	1	1	1	0	0	
503		.8875	1	1	1	0	1	1	1	1	1	0	0	
504		82.900	0	0	0	1	1	1	1	1	1	0	0	
505		.9125	1	0	0	1	1	1	1	1	1	0	0	
506		.925	0	1	0	1	1	1	1	1	1	0	0	
507		.9375	1	1	0	1	1	1	1	1	1	0	0	
508		.950	0	0	1	1	1	1	1	1	1	0	0	
509		.9625	1	0	1	1	1	1	1	1	1	0	0	
510		.975	0	1	1		1	1	1		1	0	0	
LL 511		.9875	1	1	1		1	1	1		1	0	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
			0	1	0	0	0	0	0	0	0	0	1	
LH 0			0	0	0	0	0	0	0	0	0	0	1	0
1			1	0	0	0	0	0	0	0	0	0	1	0
2			0	1	0	0	0	0	0	0	0	0	1	0
3			1	1	0	0	0	0	0	0	0	0	1	0
4			0	0	1	0	0	0	0	0	0	0	1	0
5			1	0	1	0	0	0	0	0	0	0	1	0
6			0	1	1	0	0	0	0	0	0	0	1	0
7			1	1	1	0	0	0	0	0	0	0	1	0
8			0	0	0	1	0	0	0	0	0	0	1	0
9			1	0	0	1	0	0	0	0	0	0	1	0
10			0	1	0	1	0	0	0	0	0	0	1	0
11			1	1	0	1	0	0	0	0	0	0	1	0
12			0	0	1	1	0	0	0	0	0	0	1	0
13			1	0	1	1	0	0	0	0	0	0	1	0
14			0	1	1	1	0	0	0	0	0	0	1	0
15			1	1	1	1	0	0	0	0	0	0	1	0
16			0	0	0	0	1	0	0	0	0	0	1	0
17			1	0	0	0	1	0	0	0	0	0	1	0
18			0	1	0	0	1	0	0	0	0	0	1	0
19			1	1	0	0	1	0	0	0	0	0	1	0
20			0	0	1	0	1	0	0	0	0	0	1	0
21			1	0	1	0	1	0	0	0	0	0	1	0
22			0	1	1	0	1	0	0	0	0	0	1	0
23			1	1	1	0	1	0	0	0	0	0	1	0
24			0	0	0	1	1	0	0	0	0	0	1	0
25			1	0	0	1	1	0	0	0	0	0	1	0
26			0	1	0	1	1	0	0	0	0	0	1	0
27			1	1	0	1	1	0	0	0	0	0	1	0
28			0	0	1	1	1	0	0	0	0	0	1	0
29			1	0	1	1	1	0	0	0	0	0	1	0
30			0	1	1	1	1	0	0	0	0	0	1	0
31		82.9875	1	1	1	1	1	0	0	0	0	0	1	0
32		83.000	0	0	0	0	0	1	0	0	0	0	1	0
33		.0125	1	0	0	0	0	1	0	0	0	0	1	0
34		.025	0	1	0	0	0	1	0	0	0	0	1	0
35		.0375	1	1	0	0	0	1	0	0	0	0	1	0
36		.050	0	0	1	0	0	1	0	0	0	0	1	0
37		.0625	1	0	1	0	0	1	0	0	0	0	1	0
38		.075	0	1	1	0	0	1	0	0	0	0	1	0
39		.0875	1	1	1	0	0	1	0	0	0	0	1	0
40		83.100	0	0	0	1	0	1	0	0	0	0	1	0
41		.1125	1	0	0	1	0	1	0	0	0	0	1	0
42		.125	0	1	0	1	0	1	0	0	0	0	1	0
43		.1375	1	1	0	1	0	1	0	0	0	0	1	0
44		.150	0	0	1	1	0	1	0	0	0	0	1	0
45		.1625	1	0	1	1	0	1	0	0	0	0	1	0
46		.175	0	1	1	1	0	1	0	0	0	0	1	0
47		.1875	1	1	1	1	0	1	0	0	0	0	1	0
48		83.200	0	0	0	0	1	1	0	0	0	0	1	0
49		.2125	1	0	0	0	1	1	0	0	0	0	1	0
50		.225	0	1	0	0	1	1	0	0	0	0	1	0
51		.2375	1	1	0	0	1	1	0	0	0	0	1	0
52		.250	0	0	1	0	1	1	0	0	0	0	1	0
53		.2625	1	0	1	0	1	1	0	0	0	0	1	0
54		.275	0	1	1	0	1	1	0	0	0	0	1	0
55		.2875	1	1	1	0	1	1	0	0	0	0	1	0
56		83.300	0	0	0	1	1	1	0	0	0	0	1	0
57		.3125	1	0	0	1	1	1	0	0	0	0	1	0
58		.325	0	1	0	1	1	1	0	0	0	0	1	0
59		.3375	1	1	0	1	1	1	0	0	0	0	1	0
60		.350	0	0	1	1	1	1	0	0	0	0	1	0
61		.3625	1	0	1	1	1	1	0	0	0	0	1	0
62		.375	0	1	1	1	1	1	0	0	0	0	1	0
LH 63		.3875	1	1	1	1	1	1	0	0	0	0	1	0

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	N11	NOTE
LH 64		83.400	0	0	0	0	0	0	1	0	0	1	0	
65		.4125	1	0	0	0	0	0	1	0	0	1	0	
66		.425	0	1	0	0	0	0	1	0	0	1	0	
67		.4375	1	1	0	0	0	0	1	0	0	1	0	
68		.450	0	0	1	0	0	0	1	0	0	1	0	
69		.4625	1	0	1	0	0	0	1	0	0	1	0	
70		.475	0	1	1	0	0	0	1	0	0	1	0	
71		.4875	1	1	1	0	0	0	1	0	0	1	0	
72		83.500	0	0	0	1	0	0	1	0	0	1	0	
73		.5125	1	0	0	1	0	0	1	0	0	1	0	
74		.525	0	1	0	1	0	0	1	0	0	1	0	
75		.5375	1	1	0	1	0	0	1	0	0	1	0	
76		.550	0	0	1	1	0	0	1	0	0	1	0	
77		.5625	1	0	1	1	0	0	1	0	0	1	0	
78		.575	0	1	1	1	0	0	1	0	0	1	0	
79		.5875	1	1	1	1	0	0	1	0	0	1	0	
80		83.600	0	0	0	0	1	0	1	0	0	1	0	
81		.6125	1	0	0	0	1	0	1	0	0	1	0	
82		.625	0	1	0	0	1	0	1	0	0	1	0	
83		.6375	1	1	0	0	1	0	1	0	0	1	0	
84		.650	0	0	1	0	1	0	1	0	0	1	0	
85		.6625	1	0	1	0	1	0	1	0	0	1	0	
86		.675	0	1	1	0	1	0	1	0	0	1	0	
87		.6875	1	1	1	0	1	0	1	0	0	1	0	
88		83.700	0	0	0	1	1	0	1	0	0	1	0	
89		.7125	1	0	0	1	1	0	1	0	0	1	0	
90		.725	0	1	0	1	1	0	1	0	0	1	0	
91		.7375	1	1	0	1	1	0	1	0	0	1	0	
92		.750	0	0	1	1	1	0	1	0	0	1	0	
93		.7625	1	0	1	1	1	0	1	0	0	1	0	
94		.775	0	1	1	1	0	1	0	0	0	1	0	
95		.7875	1	1	1	1	1	0	1	0	0	1	0	
96		83.800	0	0	0	0	0	1	1	0	0	1	0	
97		.8125	1	0	0	0	0	1	1	0	0	1	0	
98		.825	0	1	0	0	0	1	1	0	0	1	0	
99		.8375	1	1	0	0	0	1	1	0	0	1	0	
100		.850	0	0	1	0	0	1	1	0	0	1	0	
101		.8625	1	0	1	0	0	1	1	0	0	1	0	
102		.875	0	1	1	0	0	1	1	0	0	1	0	
103		.8875	1	1	1	0	0	1	1	0	0	1	0	
104		83.900	0	0	0	1	0	1	1	0	0	1	0	
105		.9125	1	0	0	1	0	1	1	0	0	1	0	
106		.925	0	1	0	1	0	1	1	0	0	1	0	
107		.9375	1	1	0	1	0	1	1	0	0	1	0	
108		.950	0	0	1	1	0	1	1	0	0	1	0	
109		.9625	1	0	1	1	0	1	1	0	0	1	0	
110		.975	0	1	1	1	0	1	1	0	0	1	0	
111		.9875	1	1	1	1	0	1	1	0	0	1	0	
112		84.000	0	0	0	0	1	1	1	0	0	1	0	
113		.0125	1	0	0	0	1	1	1	0	0	1	0	
114		.025	0	1	0	0	1	1	1	0	0	1	0	
115		.0375	1	1	0	0	1	1	1	0	0	1	0	
116		.050	0	0	1	0	1	1	1	0	0	1	0	
117		.0625	1	0	1	0	1	1	1	0	0	1	0	
118		.075	0	1	1	0	1	1	1	0	0	1	0	
119		.0875	1	1	1	0	1	1	1	0	0	1	0	
120		84.100	0	0	0	1	1	1	1	0	0	1	0	
121		.1125	1	0	0	1	1	1	1	0	0	1	0	
122		.125	0	1	0	1	1	1	1	0	0	1	0	
123		.1375	1	1	0	1	1	1	1	0	0	1	0	
124		.150	0	0	1	1	1	1	1	0	0	1	0	
125		.1625	1	0	1	1	1	1	1	0	0	1	0	
126		.175	0	1	1		1	1	1		0	1	0	
LH 127		.1875	1	1	1		1	1	1		0	1	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
LH 128		84. 200	0	0	0	0	0	0	0	1	0	1	0	
129		. 2125	1	0	0	0	0	0	0	1	0	1	0	
130		. 225	0	1	0	0	0	0	0	1	0	1	0	
131		. 2375	1	1	0	0	0	0	0	1	0	1	0	
132		. 250	0	0	1	0	0	0	0	1	0	1	0	
133		. 2625	1	0	1	0	0	0	0	1	0	1	0	
134		. 275	0	1	1	0	0	0	0	1	0	1	0	
135		. 2875	1	1	1	0	0	0	0	1	0	1	0	
136		84. 300	0	0	0	1	0	0	0	1	0	1	0	
137		. 3125	1	0	0	1	0	0	0	1	0	1	0	
138		. 325	0	1	0	1	0	0	0	1	0	1	0	
139		. 3375	1	1	0	1	0	0	0	1	0	1	0	
140		. 350	0	0	1	1	0	0	0	1	0	1	0	
141		. 3625	1	0	1	1	0	0	0	1	0	1	0	
142		. 375	0	1	1	1	0	0	0	1	0	1	0	
143		. 3875	1	1	1	1	0	0	0	1	0	1	0	
144		84. 400	0	0	0	0	1	0	0	1	0	1	0	
145		. 4125	1	0	0	0	1	0	0	1	0	1	0	
146		. 425	0	1	0	0	1	0	0	1	0	1	0	
147		. 4375	1	1	0	0	1	0	0	1	0	1	0	
148		. 450	0	0	1	0	1	0	0	1	0	1	0	
149		. 4625	1	0	1	0	1	0	0	1	0	1	0	
150		. 475	0	1	1	0	1	0	0	1	0	1	0	
151		. 4875	1	1	1	0	1	0	0	1	0	1	0	
152		84. 500	0	0	0	1	1	0	0	1	0	1	0	
153		. 5125	1	0	0	1	1	0	0	1	0	1	0	
154		. 525	0	1	0	1	1	0	0	1	0	1	0	
155		. 5375	1	1	0	1	1	0	0	1	0	1	0	
156		. 550	0	0	1	1	1	0	0	1	0	1	0	
157		. 5625	1	0	1	1	1	0	0	1	0	1	0	
158		. 575	0	1	1	1	1	0	0	1	0	1	0	
159		. 5875	1	1	1	1	1	0	0	1	0	1	0	
160		84. 600	0	0	0	0	0	1	0	1	0	1	0	
161		. 6125	1	0	0	0	0	1	0	1	0	1	0	
162		. 625	0	1	0	0	0	1	0	1	0	1	0	
163		. 6375	1	1	0	0	0	1	0	1	0	1	0	
164		. 650	0	0	1	0	0	1	0	1	0	1	0	
165		. 6625	1	0	1	0	0	1	0	1	0	1	0	
166		. 675	0	1	1	0	0	1	0	1	0	1	0	
167		. 6875	1	1	1	0	0	1	0	1	0	1	0	
168		84. 700	0	0	0	1	0	1	0	1	0	1	0	
169		. 7125	1	0	0	1	0	1	0	1	0	1	0	
170		. 725	0	1	0	1	0	1	0	1	0	1	0	
171		. 7375	1	1	0	1	0	1	0	1	0	1	0	
172		. 750	0	0	1	1	0	1	0	1	0	1	0	
173		. 7625	1	0	1	1	0	1	0	1	0	1	0	
174		. 775	0	1	1	1	0	1	0	1	0	1	0	
175		. 7875	1	1	1	1	0	1	0	1	0	1	0	
176		84. 800	0	0	0	0	1	1	0	1	0	1	0	
177		. 8125	1	0	0	0	1	1	0	1	0	1	0	
178		. 825	0	1	0	0	1	1	0	1	0	1	0	
179		. 8375	1	1	0	0	1	1	0	1	0	1	0	
180		. 850	0	0	1	0	1	1	0	1	0	1	0	
181		. 8625	1	0	1	0	1	1	0	1	0	1	0	
182		. 875	0	1	1	0	1	1	0	1	0	1	0	
183		. 8875	1	1	1	0	1	1	0	1	0	1	0	
184		84. 900	0	0	0	1	1	1	0	1	0	1	0	
185		. 9125	1	0	0	1	1	1	0	1	0	1	0	
186		. 925	0	1	0	1	1	1	0	1	0	1	0	
187		. 9375	1	1	0	1	1	1	0	1	0	1	0	
188		. 950	0	0	1	1	1	1	0	1	0	1	0	
189		. 9625	1	0	1	1	1	1	0	1	0	1	0	
190		. 975	0	1	1	1	1	1	0	1	0	1	0	
LH 191		. 9875	1	1	1	1	1	1	0	1	0	1	0	

PANEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H L N11	NOTE
LH 192		85.000	0	0	0	0	0	0	1	1	0	1	0	
193		.0125	1	0	0	0	0	0	1	1	0	1	0	
194		.025	0	1	0	0	0	0	1	1	0	1	0	
195		.0375	1	1	0	0	0	0	1	1	0	1	0	
196		.050	0	0	1	0	0	0	1	1	0	1	0	
197		.0625	1	0	1	0	0	0	1	1	0	1	0	
198		.075	0	1	1	0	0	0	1	1	0	1	0	
199		.0875	1	1	1	0	0	0	1	1	0	1	0	
200		85.100	0	0	0	1	0	0	1	1	0	1	0	
201		.1125	1	0	0	1	0	0	1	1	0	1	0	
202		.125	0	1	0	1	0	0	1	1	0	1	0	
203		.1375	1	1	0	1	0	0	1	1	0	1	0	
204		.150	0	0	1	1	0	0	1	1	0	1	0	
205		.1625	1	0	1	1	0	0	1	1	0	1	0	
206		.175	0	1	1	1	0	0	1	1	0	1	0	
207		.1875	1	1	1	1	0	0	1	1	0	1	0	
208		85.200	0	0	0	0	1	0	1	1	0	1	0	
209		.2125	1	0	0	0	1	0	1	1	0	1	0	
210		.225	0	1	0	0	1	0	1	1	0	1	0	
211		.2375	1	1	0	0	1	0	1	1	0	1	0	
212		.250	0	0	1	0	1	0	1	1	0	1	0	
213		.2625	1	0	1	0	1	0	1	1	0	1	0	
214		.275	0	1	1	0	1	0	1	1	0	1	0	
215		.2875	1	1	1	0	1	0	1	1	0	1	0	
216		85.300	0	0	0	1	1	0	1	1	0	1	0	
217		.3125	1	0	0	1	1	0	1	1	0	1	0	
218		.325	0	1	0	1	1	0	1	1	0	1	0	
219		.3375	1	1	0	1	1	0	1	1	0	1	0	
220		.350	0	0	1	1	1	0	1	1	0	1	0	
221		.3625	1	0	1	1	1	0	1	1	0	1	0	
222		.375	0	1	1	1	1	0	1	1	0	1	0	
223		.3875	1	1	1	1	1	0	1	1	0	1	0	
224		85.400	0	0	0	0	0	1	1	1	0	1	0	
225		.4125	1	0	0	0	0	1	1	1	0	1	0	
226		.425	0	1	0	0	0	1	1	1	0	1	0	
227		.4375	1	1	0	0	0	1	1	1	0	1	0	
228		.450	0	0	1	0	0	1	1	1	0	1	0	
229		.4625	1	0	1	0	0	1	1	1	0	1	0	
230		.475	0	1	1	0	0	1	1	1	0	1	0	
231		.4875	1	1	1	0	0	1	1	1	0	1	0	
232		85.500	0	0	0	1	0	1	1	1	0	1	0	
233		.5125	1	0	0	1	0	1	1	1	0	1	0	
234		.525	0	1	0	1	0	1	1	1	0	1	0	
235		.5375	1	1	0	1	0	1	1	1	0	1	0	
236		.550	0	0	1	1	0	1	1	1	0	1	0	
237		.5625	1	0	1	1	0	1	1	1	0	1	0	
238		.575	0	1	1	1	0	1	1	1	0	1	0	
239		.5875	1	1	1	1	0	1	1	1	0	1	0	
240		85.600	0	0	0	0	1	1	1	1	0	1	0	
241		.6125	1	0	0	0	1	1	1	1	0	1	0	
242		.625	0	1	0	0	1	1	1	1	0	1	0	
243		.6375	1	1	0	0	1	1	1	1	0	1	0	
244		.650	0	0	1	0	1	1	1	1	0	1	0	
245		.6625	1	0	1	0	1	1	1	1	0	1	0	
246		.675	0	1	1	0	1	1	1	1	0	1	0	
247		.6875	1	1	1	0	1	1	1	1	0	1	0	
248		85.700	0	0	0	1	1	1	1	1	0	1	0	
249		.7125	1	0	0	1	1	1	1	1	0	1	0	
250		.725	0	1	0	1	1	1	1	1	0	1	0	
251		.7375	1	1	0	1	1	1	1	1	0	1	0	
252		.750	0	0	1	1	1	1	1	1	0	1	0	
253		.7625	1	0	1	1	1	1	1	1	0	1	0	
254		.775	0	1	1		1	1	1		0	1	0	
LH 255		.7875	1	1	1		1	1	1		0	1	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
LH 256		85. 800	0	0	0	0	0	0	0	0	1	1	0	
257		. 8125	1	0	0	0	0	0	0	0	1	1	0	
258		. 825	0	1	0	0	0	0	0	0	1	1	0	
259		. 8375	1	1	0	0	0	0	0	0	1	1	0	
260		. 850	0	0	1	0	0	0	0	0	1	1	0	
261		. 8625	1	0	1	0	0	0	0	0	1	1	0	
262		. 875	0	1	1	0	0	0	0	0	1	1	0	
263		. 8875	1	1	1	0	0	0	0	0	1	1	0	
264		85. 900	0	0	0	1	0	0	0	0	1	1	0	
265		. 9125	1	0	0	1	0	0	0	0	1	1	0	
266		. 925	0	1	0	1	0	0	0	0	1	1	0	
267		. 9375	1	1	0	1	0	0	0	0	1	1	0	
268		. 950	0	0	1	1	0	0	0	0	1	1	0	
269		. 9625	1	0	1	1	0	0	0	0	1	1	0	
270		. 975	0	1	1	1	0	0	0	0	1	1	0	
271		. 9875	1	1	1	1	0	0	0	0	1	1	0	
272		86. 000	0	0	0	0	1	0	0	0	1	1	0	
273		. 0125	1	0	0	0	1	0	0	0	1	1	0	
274		. 025	0	1	0	0	1	0	0	0	1	1	0	
275		. 0375	1	1	0	0	1	0	0	0	1	1	0	
276		. 050	0	0	1	0	1	0	0	0	1	1	0	
277		. 0625	1	0	1	0	1	0	0	0	1	1	0	
278		. 075	0	1	1	0	1	0	0	0	1	1	0	
279		. 0875	1	1	1	0	1	0	0	0	1	1	0	
280		86. 100	0	0	0	1	1	0	0	0	1	1	0	
281		. 1125	1	0	0	1	1	0	0	0	1	1	0	
282		. 125	0	1	0	1	1	0	0	0	1	1	0	
283		. 1375	1	1	0	1	1	0	0	0	1	1	0	
284		. 150	0	0	1	1	1	0	0	0	1	1	0	
285		. 1625	1	0	1	1	1	0	0	0	1	1	0	
286		. 175	0	1	1	1	1	0	0	0	1	1	0	
287		. 1875	1	1	1	1	1	0	0	0	1	1	0	
288		86. 200	0	0	0	0	0	1	0	0	1	1	0	
289		. 2125	1	0	0	0	0	1	0	0	1	1	0	
290		. 225	0	1	0	0	0	1	0	0	1	1	0	
291		. 2375	1	1	0	0	0	1	0	0	1	1	0	
292		. 250	0	0	1	0	0	1	0	0	1	1	0	
293		. 2625	1	0	1	0	0	1	0	0	1	1	0	
294		. 275	0	1	1	0	0	1	0	0	1	1	0	
295		. 2875	1	1	1	0	0	1	0	0	1	1	0	
296		86. 300	0	0	0	1	0	1	0	0	1	1	0	
297		. 3125	1	0	0	1	0	1	0	0	1	1	0	
298		. 325	0	1	0	1	0	1	0	0	1	1	0	
299		. 3375	1	1	0	1	0	1	0	0	1	1	0	
300		. 350	0	0	1	1	0	1	0	0	1	1	0	
301		. 3625	1	0	1	1	0	1	0	0	1	1	0	
302		. 375	0	1	1	1	0	1	0	0	1	1	0	
303		. 3875	1	1	1	1	0	1	0	0	1	1	0	
304		86. 400	0	0	0	0	1	1	0	0	1	1	0	
305		. 4125	1	0	0	0	1	1	0	0	1	1	0	
306		. 425	0	1	0	0	1	1	0	0	1	1	0	
307		. 4375	1	1	0	0	1	1	0	0	1	1	0	
308		. 450	0	0	1	0	1	1	0	0	1	1	0	
309		. 4625	1	0	1	0	1	1	0	0	1	1	0	
310		. 475	0	1	1	0	1	1	0	0	1	1	0	
311		. 4875	1	1	1	0	1	1	0	0	1	1	0	
312		86. 500	0	0	0	1	1	1	0	0	1	1	0	
313		. 5125	1	0	0	1	1	1	0	0	1	1	0	
314		. 525	0	1	0	1	1	1	0	0	1	1	0	
315		. 5375	1	1	0	1	1	1	0	0	1	1	0	
316		. 550	0	0	1	1	1	1	0	0	1	1	0	
317		. 5625	1	0	1	1	1	1	0	0	1	1	0	
318		. 575	0	1	1	1	1	1	0	0	1	1	0	
LH 319		. 5875	1	1	1	1	1	1	0	0	1	1	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H.L N11	NOTE
LH 320		86.600	0	0	0	0	0	0	1	0	1	1	0	
321		.6125	1	0	0	0	0	0	1	0	1	1	0	
322		.625	0	1	0	0	0	0	1	0	0	1	1	0
323		.6375	1	1	0	0	0	0	1	0	1	1	0	
324		.650	0	0	1	0	0	0	1	0	1	1	0	
325		.6625	1	0	1	0	0	0	1	0	1	1	0	
326		.675	0	1	1	0	0	0	1	0	1	1	0	
327		.6875	1	1	1	0	0	0	1	0	1	1	0	
328		86.700	0	0	0	1	0	0	1	0	1	1	0	
329		.7125	1	0	0	1	0	0	1	0	1	1	0	
330		.725	0	1	0	1	0	0	1	0	1	1	0	
331		.7375	1	1	0	1	0	0	1	0	1	1	0	
332		.750	0	0	1	1	0	0	1	0	1	1	0	
333		.7625	1	0	1	1	0	0	1	0	1	1	0	
334		.775	0	1	1	1	0	0	1	0	1	1	0	
335		.7875	1	1	1	1	0	0	1	0	1	1	0	
336		86.800	0	0	0	0	1	0	1	0	1	1	0	
337		.8125	1	0	0	0	1	0	1	0	1	1	0	
338		.825	0	1	0	0	1	0	1	0	1	1	0	
339		.8375	1	1	0	0	1	0	1	0	1	1	0	
340		.850	0	0	1	0	1	0	1	0	1	1	0	
341		.8625	1	0	1	0	1	0	1	0	1	1	0	
342		.875	0	1	1	0	1	0	1	0	1	1	0	
343		.8875	1	1	1	0	1	0	1	0	1	1	0	
344		86.900	0	0	0	1	1	0	1	0	1	1	0	
345		.9125	1	0	0	1	1	0	1	0	1	1	0	
346		.925	0	1	0	1	1	0	1	0	1	1	0	
347		.9375	1	1	0	1	1	0	1	0	1	1	0	
348		.950	0	0	1	1	1	0	1	0	1	1	0	
349		.9625	1	0	1	1	1	0	1	0	1	1	0	
350		.975	0	1	1	1	1	0	1	0	1	1	0	
351		.9875	1	1	1	1	1	0	1	0	1	1	0	
352		87.000	0	0	0	0	0	1	1	0	1	1	0	
353		.0125	1	0	0	0	0	1	1	0	1	1	0	
354		.025	0	1	0	0	0	1	1	0	1	1	0	
355		.0375	1	1	0	0	0	1	1	0	1	1	0	
356		.050	0	0	1	0	0	1	1	0	1	1	0	
357		.0625	1	0	1	0	0	1	1	0	1	1	0	
358		.075	0	1	1	0	0	1	1	0	1	1	0	
359		.0875	1	1	1	0	0	1	1	0	1	1	0	
360		87.100	0	0	0	1	0	1	1	0	1	1	0	
361		.1125	1	0	0	1	0	1	1	0	1	1	0	
362		.125	0	1	0	1	0	1	1	0	1	1	0	
363		.1375	1	1	0	1	0	1	1	0	1	1	0	
364		.150	0	0	1	1	0	1	1	0	1	1	0	
365		.1625	1	0	1	1	0	1	1	0	1	1	0	
366		.175	0	1	1	1	0	1	1	0	1	1	0	
367		.1875	1	1	1	1	0	1	1	0	1	1	0	
368		87.200	0	0	0	0	1	1	1	0	1	1	0	
369		.2125	1	0	0	0	1	1	1	0	1	1	0	
370		.225	0	1	0	0	1	1	1	0	1	1	0	
371		.2375	1	1	0	0	1	1	1	0	1	1	0	
372		.250	0	0	1	0	1	1	1	0	1	1	0	
373		.2625	1	0	1	0	1	1	1	0	1	1	0	
374		.275	0	1	1	0	1	1	1	0	1	1	0	
375		.2875	1	1	1	0	1	1	1	0	1	1	0	
376		87.300	0	0	0	1	1	1	1	0	1	1	0	
377		.3125	1	0	0	1	1	1	1	0	1	1	0	
378		.325	0	1	0	1	1	1	1	0	1	1	0	
379		.3375	1	1	0	1	1	1	1	0	1	1	0	
380		.350	0	0	1	1	1	1	1	0	1	1	0	
381		.3625	1	0	1	1	1	1	1	0	1	1	0	
382		.375	0	1	1	1	1	1	1	0	1	1	0	
LH 383		.3875	1	1	1	1	1	1	1	0	1	1	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
LH 384		87. 400	0	0	0	0	0	0	0	1	1	1	0	
385		. 4125	1	0	0	0	0	0	0	1	1	1	0	
386		. 425	0	1	0	0	0	0	0	1	1	1	0	
387		. 4375	1	1	0	0	0	0	0	1	1	1	0	
388		. 450	0	0	1	0	0	0	0	1	1	1	0	
389		. 4625	1	0	1	0	0	0	0	1	1	1	0	
390		. 475	0	1	1	0	0	0	0	1	1	1	0	
391		. 4875	1	1	1	0	0	0	0	1	1	1	0	
392		87. 500	0	0	0	1	0	0	0	1	1	1	0	
393		. 5125	1	0	0	1	0	0	0	1	1	1	0	
394		. 525	0	1	0	1	0	0	0	1	1	1	0	
395		. 5375	1	1	0	1	0	0	0	1	1	1	0	
396		. 550	0	0	1	1	0	0	0	1	1	1	0	
397		. 5625	1	0	1	1	0	0	0	1	1	1	0	
398		. 575	0	1	1	1	0	0	0	1	1	1	0	
399		. 5875	1	1	1	1	0	0	0	1	1	1	0	
400		87. 600	0	0	0	0	1	0	0	1	1	1	0	
401		. 6125	1	0	0	0	1	0	0	1	1	1	0	
402		. 625	0	1	0	0	1	0	0	1	1	1	0	
403		. 6375	1	1	0	0	1	0	0	1	1	1	0	
404		. 650	0	0	1	0	1	0	0	1	1	1	0	
405		. 6625	1	0	1	0	1	0	0	1	1	1	0	
406		. 675	0	1	1	0	1	0	0	1	1	1	0	
407		. 6875	1	1	1	0	1	0	0	1	1	1	0	
408		87. 700	0	0	0	1	1	0	0	1	1	1	0	
409		. 7125	1	0	0	1	1	0	0	1	1	1	0	
410		. 725	0	1	0	1	1	0	0	1	1	1	0	
411		. 7375	1	1	0	1	1	0	0	1	1	1	0	
412		. 750	0	0	1	1	1	0	0	1	1	1	0	
413		. 7625	1	0	1	1	1	0	0	1	1	1	0	
414		. 775	0	1	1	1	1	0	0	1	1	1	0	
415		. 7875	1	1	1	1	1	0	0	1	1	1	0	
416		87. 800	0	0	0	0	0	1	0	1	1	1	0	
417		. 8125	1	0	0	0	0	1	0	1	1	1	0	
418		. 825	0	1	0	0	0	1	0	1	1	1	0	
419		. 8375	1	1	0	0	0	1	0	1	1	1	0	
420		. 850	0	0	1	0	0	1	0	1	1	1	0	
421		. 8625	1	0	1	0	0	1	0	1	1	1	0	
422		. 875	0	1	1	0	0	1	0	1	1	1	0	
423		. 8875	1	1	1	0	0	1	0	1	1	1	0	
424		87. 900	0	0	0	1	0	1	0	1	1	1	0	
425		. 9125	1	0	0	1	0	1	0	1	1	1	0	
426		. 925	0	1	0	1	0	1	0	1	1	1	0	
427		. 9375	1	1	0	1	0	1	0	1	1	1	0	
428		. 950	0	0	1	1	0	1	0	1	1	1	0	
429		. 9625	1	0	1	1	0	1	0	1	1	1	0	
430		. 975	0	1	1	1	0	1	0	1	1	1	0	
431		. 9875	1	1	1	1	0	1	0	1	1	1	0	
432		88. 000	0	0	0	0	1	1	0	1	1	1	0	
433		. 0125	1	0	0	0	1	1	0	1	1	1	0	
434		. 025	0	1	0	0	1	1	0	1	1	1	0	
435		. 0375	1	1	0	0	1	1	0	1	1	1	0	
436		. 050	0	0	1	0	1	1	0	1	1	1	0	
437		. 0625	1	0	1	0	1	1	0	1	1	1	0	
438		. 075	0	1	1	0	1	1	0	1	1	1	0	
439		. 0875	1	1	1	0	1	1	0	1	1	1	0	
440		88. 100	0	0	0	1	1	1	0	1	1	1	0	
441		. 1125	1	0	0	1	1	1	0	1	1	1	0	
442		. 125	0	1	0	1	1	1	0	1	1	1	0	
443		. 1375	1	1	0	1	1	1	0	1	1	1	0	
444		. 150	0	0	1	1	1	1	0	1	1	1	0	
445		. 1625	1	0	1	1	1	1	0	1	1	1	0	
446		. 175	0	1	1	1	1	1	0	1	1	1	0	
LH 447		. 1875	1	1	1	1	1	1	0	1	1	1	0	

CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H L N11	NOTE
LH 448		88. 200	0	0	0	0	0	0	1	1	1	1	0	
449		. 2125	1	0	0	0	0	0	1	1	1	1	0	
450		. 225	0	1	0	0	0	0	1	1	1	1	0	
451		. 2375	1	1	0	0	0	0	1	1	1	1	0	
452		. 250	0	0	1	0	0	0	1	1	1	1	0	
453		. 2625	1	0	1	0	0	0	1	1	1	1	0	
454		. 275	0	1	1	0	0	0	1	1	1	1	0	
455		. 2875	1	1	1	0	0	0	1	1	1	1	0	
456		88. 300	0	0	0	1	0	0	1	1	1	1	-0	
457		. 3125	1	0	0	1	0	0	1	1	1	1	0	
458		. 325	0	1	0	1	0	0	1	1	1	1	0	
459		. 3375	1	1	0	1	0	0	1	1	1	1	0	
460		. 350	0	0	1	1	0	0	1	1	1	1	0	
461		. 3625	1	0	1	1	0	0	1	1	1	1	0	
462		. 375	0	1	1	1	0	0	1	1	1	1	0	
463		. 3875	1	1	1	1	0	0	1	1	1	1	0	
464		88. 400	0	0	0	0	1	0	1	1	1	1	0	
465		. 4125	1	0	0	0	1	0	1	1	1	1	0	
466		. 425	0	1	0	0	1	0	1	1	1	1	0	
467		. 4375	1	1	0	0	1	0	1	1	1	1	0	
468		. 450	0	0	1	0	1	0	1	1	1	1	0	
469		. 4625	1	0	1	0	1	0	1	1	1	1	0	
470		. 475	0	1	1	0	1	0	1	1	1	1	0	
471		. 4875	1	1	1	0	1	0	1	1	1	1	0	
472		88. 500	0	0	0	1	1	0	1	1	1	1	0	
473		. 5125	1	0	0	1	1	0	1	1	1	1	0	
474		. 525	0	1	0	1	1	0	1	1	1	1	0	
475		. 5375	1	1	0	1	1	0	1	1	1	1	0	
476		. 550	0	0	1	1	1	0	1	1	1	1	0	
477		. 5625	1	0	1	1	1	0	1	1	1	1	0	
478		. 575	0	1	1	1	1	0	1	1	1	1	0	
479		. 5875	1	1	1	1	1	0	1	1	1	1	0	
480		88. 600	0	0	0	0	0	1	1	1	1	1	0	
481		. 6125	1	0	0	0	0	1	1	1	1	1	0	
482		. 625	0	1	0	0	0	1	1	1	1	1	0	
483		. 6375	1	1	0	0	0	1	1	1	1	1	0	
484		. 650	0	0	1	0	0	1	1	1	1	1	0	
485		. 6625	1	0	1	0	0	1	1	1	1	1	0	
486		. 675	0	1	1	0	0	1	1	1	1	1	0	
487		. 6875	1	1	1	0	0	1	1	1	1	1	0	
488		88. 700	0	0	0	1	0	1	1	1	1	1	0	
489		. 7125	1	0	0	1	0	1	1	1	1	1	0	
490		. 725	0	1	0	1	0	1	1	1	1	1	0	
491		. 7375	1	1	0	1	0	1	1	1	1	1	0	
492		. 750	0	0	1	1	0	1	1	1	1	1	0	
493		. 7625	1	0	1	1	0	1	1	1	1	1	0	
494		. 775	0	1	1	1	0	1	1	1	1	1	0	
495		. 7875	1	1	1	1	0	1	1	1	1	1	0	
496		88. 800	0	0	0	0	1	1	1	1	1	1	0	
497		. 8125	1	0	0	0	1	1	1	1	1	1	0	
498		. 825	0	1	0	0	1	1	1	1	1	1	0	
499		. 8375	1	1	0	0	1	1	1	1	1	1	0	
500		. 850	0	0	1	0	1	1	1	1	1	1	0	
501		. 8625	1	0	1	0	1	1	1	1	1	1	0	
502		. 875	0	1	1	0	1	1	1	1	1	1	0	
503		. 8875	1	1	1	0	1	1	1	1	1	1	0	
504		88. 900	0	0	0	1	1	1	1	1	1	1	0	
505		. 9125	1	0	0	1	1	1	1	1	1	1	0	
506		. 925	0	1	0	1	1	1	1	1	1	1	0	
507		. 9375	1	1	0	1	1	1	1	1	1	1	0	
508		. 950	0	0	1	1	1	1	1	1	1	1	0	
509		. 9625	1	0	1	1	1	1	1	1	1	1	0	
510		. 975	0	1	1	1	1	1	1	1	1	1	0	
LH 511		. 9875	1	1	1	1	1	1	1	1	1	1	0	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HL 0			0	0	0	0	0	0	0	0	0	0	1	
1			1	0	0	0	0	0	0	0	0	0	1	
2			0	1	0	0	0	0	0	0	0	0	1	
3			1	1	0	0	0	0	0	0	0	0	1	
4			0	0	1	0	0	0	0	0	0	0	1	
5			1	0	1	0	0	0	0	0	0	0	1	
6			0	1	1	0	0	0	0	0	0	0	1	
7			1	1	1	0	0	0	0	0	0	0	1	
8			0	0	0	1	0	0	0	0	0	0	1	
9			1	0	0	1	0	0	0	0	0	0	1	
10			0	1	0	1	0	0	0	0	0	0	1	
11			1	1	0	1	0	0	0	0	0	0	1	
12			0	0	1	1	0	0	0	0	0	0	1	
13			1	0	1	1	0	0	0	0	0	0	1	
14			0	1	1	1	0	0	0	0	0	0	1	
15			1	1	1	1	0	0	0	0	0	0	1	
16			0	0	0	0	1	0	0	0	0	0	1	
17			1	0	0	0	1	0	0	0	0	0	1	
18			0	1	0	0	1	0	0	0	0	0	1	
19			1	1	0	0	1	0	0	0	0	0	1	
20			0	0	1	0	1	0	0	0	0	0	1	
21			1	0	1	0	1	0	0	0	0	0	1	
22			0	1	1	0	1	0	0	0	0	0	1	
23			1	1	1	0	1	0	0	0	0	0	1	
24			0	0	0	1	1	0	0	0	0	0	1	
25			1	0	0	1	1	0	0	0	0	0	1	
26			0	1	0	1	1	0	0	0	0	0	1	
27			1	1	0	1	1	0	0	0	0	0	1	
28			0	0	1	1	1	0	0	0	0	0	1	
29			1	0	1	1	1	0	0	0	0	0	1	
30			0	1	1	1	1	0	0	0	0	0	1	
31		160.1875	1	1	1	1	1	0	0	0	0	0	1	
32		160.200	0	0	0	0	1	0	0	0	0	0	1	
33		2125	1	0	0	0	0	1	0	0	0	0	1	
34		225	0	1	0	0	0	1	0	0	0	0	1	
35		2375	1	1	0	0	0	1	0	0	0	0	1	
36		250	0	0	1	0	0	1	0	0	0	0	1	
37		2625	1	0	1	0	0	1	0	0	0	0	1	
38		275	0	1	1	0	0	1	0	0	0	0	1	
39		2875	1	1	1	0	0	1	0	0	0	0	1	
40		160.300	0	0	0	1	0	1	0	0	0	0	1	
41		3125	1	0	0	1	0	1	0	0	0	0	1	
42		325	0	1	0	1	0	1	0	0	0	0	1	
43		3375	1	1	0	1	0	1	0	0	0	0	1	
44		350	0	0	1	1	0	1	0	0	0	0	1	
45		3625	1	0	1	1	0	1	0	0	0	0	1	
46		375	0	1	1	1	0	1	0	0	0	0	1	
47		3875	1	1	1	1	0	1	0	0	0	0	1	
48		160.400	0	0	0	0	1	1	0	0	0	0	1	
49		4125	1	0	0	0	1	1	0	0	0	0	1	
50		425	0	1	0	0	1	1	0	0	0	0	1	
51		4375	1	1	0	0	1	1	0	0	0	0	1	
52		450	0	0	1	0	1	1	0	0	0	0	1	
53		4625	1	0	1	0	1	1	0	0	0	0	1	
54		475	0	1	1	0	1	1	0	0	0	0	1	
55		4875	1	1	1	0	1	1	0	0	0	0	1	
56		160.500	0	0	0	1	1	1	0	0	0	0	1	
57		5125	1	0	0	1	1	1	0	0	0	0	1	
58		525	0	1	0	1	1	1	0	0	0	0	1	
59		5375	1	1	0	1	1	1	0	0	0	0	1	
60		550	0	0	1	1	1	1	0	0	0	0	1	
61		5625	1	0	1	1	1	1	0	0	0	0	1	
62		575	0	1	1	1	1	1	0	0	0	0	1	
HL 63		5875	1	1	1	1	1	1	0	0	0	0	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H.L N11	NOTE
HL 64		160. 600	0	0	0	0	0	0	1	0	0	0	1	
65		. 6125	1	0	0	0	0	0	1	0	0	0	1	
66		. 625	0	1	0	0	0	0	1	0	0	0	1	
67		. 6375	1	1	0	0	0	0	1	0	0	0	1	
68		. 650	0	0	1	0	0	0	1	0	0	0	1	
69		. 6625	1	0	1	0	0	0	1	0	0	0	1	
70		. 675	0	1	1	0	0	0	1	0	0	0	1	
71		. 6875	1	1	1	0	0	0	1	0	0	0	1	
72		160. 700	0	0	0	1	0	0	1	0	0	0	1	
73		. 7125	1	0	0	1	0	0	1	0	0	0	1	
74		. 725	0	1	0	1	0	0	1	0	0	0	1	
75		. 7375	1	1	0	1	0	0	1	0	0	0	1	
76		. 750	0	0	1	1	0	0	1	0	0	0	1	
77		. 7625	1	0	1	1	0	0	1	0	0	0	1	
78		. 775	0	1	1	1	0	0	1	0	0	0	1	
79		. 7875	1	1	1	1	0	0	1	0	0	0	1	
80		160. 800	0	0	0	0	1	0	1	0	0	0	1	
81		. 8125	1	0	0	0	1	0	1	0	0	0	1	
82		. 825	0	1	0	0	1	0	1	0	0	0	1	
83		. 8375	1	1	0	0	1	0	1	0	0	0	1	
84		. 850	0	0	1	0	1	0	1	0	0	0	1	
85		. 8625	1	0	1	0	1	0	1	0	0	0	1	
86		. 875	0	1	1	0	1	0	1	0	0	0	1	
87		. 8875	1	1	1	0	1	0	1	0	0	0	1	
88		160. 900	0	0	0	1	1	0	1	0	0	0	1	
89		. 9125	1	0	0	1	1	0	1	0	0	0	1	
90		. 925	0	1	0	1	1	0	1	0	0	0	1	
91		. 9375	1	1	0	1	1	0	1	0	0	0	1	
92		. 950	0	0	1	1	1	0	1	0	0	0	1	
93		. 9625	1	0	1	1	1	0	1	0	0	0	1	
94		. 975	0	1	1	1	1	0	1	0	0	0	1	
95		. 9875	1	1	1	1	1	0	1	0	0	0	1	
96		161. 000	0	0	0	0	0	1	1	0	0	0	1	
97		. 0125	1	0	0	0	0	1	1	0	0	0	1	
98		. 025	0	1	0	0	0	1	1	0	0	0	1	
99		. 0375	1	1	0	0	0	1	1	0	0	0	1	
100		. 050	0	0	1	0	0	1	1	0	0	0	1	
101		. 0625	1	0	1	0	0	1	1	0	0	0	1	
102		. 075	0	1	1	0	0	1	1	0	0	0	1	
103		. 0875	1	1	1	0	0	1	1	0	0	0	1	
104		161. 100	0	0	0	1	0	1	1	0	0	0	1	
105		. 1125	1	0	0	1	0	1	1	0	0	0	1	
106		. 125	0	1	0	1	0	1	1	0	0	0	1	
107		. 1375	1	1	0	1	0	1	1	0	0	0	1	
108		. 150	0	0	1	1	0	1	1	0	0	0	1	
109		. 1625	1	0	1	1	0	1	1	0	0	0	1	
110		. 175	0	1	1	1	0	1	1	0	0	0	1	
111		. 1875	1	1	1	1	0	1	1	0	0	0	1	
112		161. 200	0	0	0	0	1	1	1	0	0	0	1	
113		. 2125	1	0	0	0	1	1	1	0	0	0	1	
114		. 225	0	1	0	0	1	1	1	0	0	0	1	
115		. 2375	1	1	0	0	1	1	1	0	0	0	1	
116		. 250	0	0	1	0	1	1	1	0	0	0	1	
117		. 2625	1	0	1	0	1	1	1	0	0	0	1	
118		. 275	0	1	1	0	1	1	1	0	0	0	1	
119		. 2875	1	1	1	0	1	1	1	0	0	0	1	
120		161. 300	0	0	0	1	1	1	1	0	0	0	1	
121		. 3125	1	0	0	1	1	1	1	0	0	0	1	
122		. 325	0	1	0	1	1	1	1	0	0	0	1	
123		. 3375	1	1	0	1	1	1	1	0	0	0	1	
124		. 350	0	0	1	1	1	1	1	0	0	0	1	
125		. 3625	1	0	1	1	1	1	1	0	0	0	1	
126		. 375	0	1	1	1	1	1	1	0	0	0	1	
HL 127		. 3875	1	1	1	1	1	1	1	0	0	0	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HL 128		161.400	0	0	0	0	0	0	0	1	0	0	1	
129		.4125	1	0	0	0	0	0	0	1	0	0	1	
130		.425	0	1	0	0	0	0	0	1	0	0	1	
131		.4375	1	1	0	0	0	0	0	1	0	0	1	
132		.450	0	0	1	0	0	0	0	1	0	0	1	
133		.4625	1	0	1	0	0	0	0	1	0	0	1	
134		.475	0	1	1	0	0	0	0	1	0	0	1	
135		.4875	1	1	1	0	0	0	0	1	0	0	1	
136		161.500	0	0	0	1	0	0	0	1	0	0	1	
137		.5125	1	0	0	1	0	0	0	1	0	0	1	
138		.525	0	1	0	1	0	0	0	1	0	0	1	
139		.5375	1	1	0	1	0	0	0	1	0	0	1	
140		.550	0	0	1	1	0	0	0	1	0	0	1	
141		.5625	1	0	1	1	0	0	0	1	0	0	1	
142		.575	0	1	1	1	0	0	0	1	0	0	1	
143		.5875	1	1	1	1	0	0	0	1	0	0	1	
144		161.600	0	0	0	0	1	0	0	1	0	0	1	
145		.6125	1	0	0	0	1	0	0	1	0	0	1	
146		.625	0	1	0	0	1	0	0	1	0	0	1	
147		.6375	1	1	0	0	1	0	0	1	0	0	1	
148		.650	0	0	1	0	1	0	0	1	0	0	1	
149		.6625	1	0	1	0	1	0	0	1	0	0	1	
150		.675	0	1	1	0	1	0	0	1	0	0	1	
151		.6875	1	1	1	0	1	0	0	1	0	0	1	
152		161.700	0	0	0	1	1	0	0	1	0	0	1	
153		.7125	1	0	0	1	1	0	0	1	0	0	1	
154		.725	0	1	0	1	1	0	0	1	0	0	1	
155		.7375	1	1	0	1	1	0	0	1	0	0	1	
156		.750	0	0	1	1	1	0	0	1	0	0	1	
157		.7625	1	0	1	1	1	0	0	1	0	0	1	
158		.775	0	1	1	1	1	0	0	1	0	0	1	
159		.7875	1	1	1	1	1	0	0	1	0	0	1	
160		161.800	0	0	0	0	0	1	0	1	0	0	1	
161		.8125	1	0	0	0	0	1	0	1	0	0	1	
162		.825	0	1	0	0	0	1	0	1	0	0	1	
163		.8375	1	1	0	0	0	1	0	1	0	0	1	
164		.850	0	0	1	0	0	1	0	1	0	0	1	
165		.8625	1	0	1	0	0	1	0	1	0	0	1	
166		.875	0	1	1	0	0	1	0	1	0	0	1	
167		.8875	1	1	1	0	0	1	0	1	0	0	1	
168		161.900	0	0	0	1	0	1	0	1	0	0	1	
169		.9125	1	0	0	1	0	1	0	1	0	0	1	
170		.925	0	1	0	1	0	1	0	1	0	0	1	
171		.9375	1	1	0	1	0	1	0	1	0	0	1	
172		.950	0	0	1	1	0	1	0	1	0	0	1	
173		.9625	1	0	1	1	0	1	0	1	0	0	1	
174		.975	0	1	1	1	0	1	0	1	0	0	1	
175		.9875	1	1	1	1	0	1	0	1	0	0	1	
176		162.000	0	0	0	0	1	1	0	1	0	0	1	
177		.0125	1	0	0	0	1	1	0	1	0	0	1	
178		.025	0	1	0	0	1	1	0	1	0	0	1	
179		.0375	1	1	0	0	1	1	0	1	0	0	1	
180		.050	0	0	1	0	1	1	0	1	0	0	1	
181		.0625	1	0	1	0	1	1	0	1	0	0	1	
182		.075	0	1	1	0	1	1	0	1	0	0	1	
183		.0875	1	1	1	0	1	1	0	1	0	0	1	
184		162.100	0	0	0	1	1	1	0	1	0	0	1	
185		.1125	1	0	0	1	1	1	0	1	0	0	1	
186		.125	0	1	0	1	1	1	0	1	0	0	1	
187		.1375	1	1	0	1	1	1	0	1	0	0	1	
188		.150	0	0	1	1	1	1	0	1	0	0	1	
189		.1625	1	0	1	1	1	1	0	1	0	0	1	
190		.175	0	1	1	1	1	1	0	1	0	0	1	
HL 191		.1875	1	1	1	1	1	1	0	1	0	0	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HL 192		162. 200	0	0	0	0	0	0	1	1	0	0	1	
193		. 2125	1	0	0	0	0	0	1	1	0	0	1	
194		. 225	0	1	0	0	0	0	1	1	0	0	1	
195		. 2375	1	1	0	0	0	0	1	1	0	0	1	
196		. 250	0	0	1	0	0	0	1	1	0	0	1	
197		. 2625	1	0	1	0	0	0	1	1	0	0	1	
198		. 275	0	1	1	0	0	0	1	1	0	0	1	
199		. 2875	1	1	1	0	0	0	1	1	0	0	1	
200		162. 300	0	0	0	1	0	0	1	1	0	0	1	
201		. 3125	1	0	0	1	0	0	1	1	0	0	1	
202		. 325	0	1	0	1	0	0	1	1	0	0	1	
203		. 3375	1	1	0	1	0	0	1	1	0	0	1	
204		. 350	0	0	1	1	0	0	1	1	0	0	1	
205		. 3625	1	0	1	1	0	0	1	1	0	0	1	
206		. 375	0	1	1	1	0	0	1	1	0	0	1	
207		. 3875	1	1	1	1	0	0	1	1	0	0	1	
208		162. 400	0	0	0	0	1	0	1	1	0	0	1	
209		. 4125	1	0	0	0	1	0	1	1	0	0	1	
210		. 425	0	1	0	0	1	0	1	1	0	0	1	
211		. 4375	1	1	0	0	1	0	1	1	0	0	1	
212		. 450	0	0	1	0	1	0	1	1	0	0	1	
213		. 4625	1	0	1	0	1	0	1	1	0	0	1	
214		. 475	0	1	1	0	1	0	1	1	0	0	1	
215		. 4875	1	1	1	0	1	0	1	1	0	0	1	
216		162. 500	0	0	0	1	1	0	1	1	0	0	1	
217		. 5125	1	0	0	1	1	0	1	1	0	0	1	
218		. 525	0	1	0	1	1	0	1	1	0	0	1	
219		. 5375	1	1	0	1	1	0	1	1	0	0	1	
220		. 550	0	0	1	1	1	0	1	1	0	0	1	
221		. 5625	1	0	1	1	1	0	1	1	0	0	1	
222		. 575	0	1	1	1	1	0	1	1	0	0	1	
223		. 5875	1	1	1	1	1	0	1	1	0	0	1	
224		162. 600	0	0	0	0	0	1	1	1	0	0	1	
225		. 6125	1	0	0	0	0	1	1	1	0	0	1	
226		. 625	0	1	0	0	0	1	1	1	0	0	1	
227		. 6375	1	1	0	0	0	1	1	1	0	0	1	
228		. 650	0	0	1	0	0	1	1	1	0	0	1	
229		. 6625	1	0	1	0	0	1	1	1	0	0	1	
230		. 675	0	1	1	0	0	1	1	1	0	0	1	
231		. 6875	1	1	1	0	0	1	1	1	0	0	1	
232		162. 700	0	0	0	1	0	1	1	1	0	0	1	
233		. 7125	1	0	0	1	0	1	1	1	0	0	1	
234		. 725	0	1	0	1	0	1	1	1	0	0	1	
235		. 7375	1	1	0	1	0	1	1	1	0	0	1	
236		. 750	0	0	1	1	0	1	1	1	0	0	1	
237		. 7625	1	0	1	1	0	1	1	1	0	0	1	
238		. 775	0	1	1	1	0	1	1	1	0	0	1	
239		. 7875	1	1	1	1	0	1	1	1	0	0	1	
240		162. 800	0	0	0	0	1	1	1	1	0	0	1	
241		. 8125	1	0	0	0	1	1	1	1	0	0	1	
242		. 825	0	1	0	0	1	1	1	1	0	0	1	
243		. 8375	1	1	0	0	1	1	1	1	0	0	1	
244		. 850	0	0	1	0	1	1	1	1	0	0	1	
245		. 8625	1	0	1	0	1	1	1	1	0	0	1	
246		. 875	0	1	1	0	1	1	1	1	0	0	1	
247		. 8875	1	1	1	0	1	1	1	1	0	0	1	
248		162. 900	0	0	0	1	1	1	1	1	0	0	1	
249		. 9125	1	0	0	1	1	1	1	1	0	0	1	
250		. 925	0	1	0	1	1	1	1	1	0	0	1	
251		. 9375	1	1	0	1	1	1	1	1	0	0	1	
252		. 950	0	0	1	1	1	1	1	1	0	0	1	
253		. 9625	1	0	1	1	1	1	1	1	0	0	1	
254		. 975	0	1	1			1	1		0	0	1	
HL 255		. 9875	1	1	1			1	1		0	0	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HL 256		163.000	0	0	0	0	0	0	0	0	1	0	1	
257		.0125	1	0	0	0	0	0	0	0	1	0	1	
258		.025	0	1	0	0	0	0	0	0	1	0	1	
259		.0375	1	1	0	0	0	0	0	0	1	0	1	
260		.050	0	0	1	0	0	0	0	0	1	0	1	
261		.0625	1	0	1	0	0	0	0	0	1	0	1	
262		.075	0	1	1	0	0	0	0	0	1	0	1	
263		.0875	1	1	1	0	0	0	0	0	1	0	1	
264		163.100	0	0	0	1	0	0	0	0	1	0	1	
265		.1125	1	0	0	1	0	0	0	0	1	0	1	
266		.125	0	1	0	1	0	0	0	0	1	0	1	
267		.1375	1	1	0	1	0	0	0	0	1	0	1	
268		.150	0	0	1	1	0	0	0	0	1	0	1	
269		.1625	1	0	1	1	0	0	0	0	1	0	1	
270		.175	0	1	1	1	0	0	0	0	1	0	1	
271		.1875	1	1	1	1	0	0	0	0	1	0	1	
272		163.200	0	0	0	0	1	0	0	0	1	0	1	
273		.2125	1	0	0	0	1	0	0	0	1	0	1	
274		.225	0	1	0	0	1	0	0	0	1	0	1	
275		.2375	1	1	0	0	1	0	0	0	1	0	1	
276		.250	0	0	1	0	1	0	0	0	1	0	1	
277		.2625	1	0	1	0	1	0	0	0	1	0	1	
278		.275	0	1	1	0	1	0	0	0	1	0	1	
279		.2875	1	1	1	0	1	0	0	0	1	0	1	
280		163.300	0	0	0	1	1	0	0	0	1	0	1	
281		.3125	1	0	0	1	1	0	0	0	1	0	1	
282		.325	0	1	0	1	1	0	0	0	1	0	1	
283		.3375	1	1	0	1	1	0	0	0	1	0	1	
284		.350	0	0	1	1	1	0	0	0	1	0	1	
285		.3625	1	0	1	1	1	0	0	0	1	0	1	
286		.375	0	1	1	1	1	0	0	0	1	0	1	
287		.3875	1	1	1	1	1	0	0	0	1	0	1	
288		163.400	0	0	0	0	0	1	0	0	1	0	1	
289		.4125	1	0	0	0	0	1	0	0	1	0	1	
290		.425	0	1	0	0	0	1	0	0	1	0	1	
291		.4375	1	1	0	0	0	1	0	0	1	0	1	
292		.450	0	0	1	0	0	1	0	0	1	0	1	
293		.4625	1	0	1	0	0	1	0	0	1	0	1	
294		.475	0	1	1	0	0	1	0	0	1	0	1	
295		.4875	1	1	1	0	0	1	0	0	1	0	1	
296		163.500	0	0	0	1	0	1	0	0	1	0	1	
297		.5125	1	0	0	1	0	1	0	0	1	0	1	
298		.525	0	1	0	1	0	1	0	0	1	0	1	
299		.5375	1	1	0	1	0	1	0	0	1	0	1	
300		.550	0	0	1	1	0	1	0	0	1	0	1	
301		.5625	1	0	1	1	0	1	0	0	1	0	1	
302		.575	0	1	1	1	0	1	0	0	1	0	1	
303		.5875	1	1	1	1	0	1	0	0	1	0	1	
304		163.600	0	0	0	0	1	1	0	0	1	0	1	
305		.6125	1	0	0	0	1	1	0	0	1	0	1	
306		.625	0	1	0	0	1	1	0	0	1	0	1	
307		.6375	1	1	0	0	1	1	0	0	1	0	1	
308		.650	0	0	1	0	1	1	0	0	1	0	1	
309		.6625	1	0	1	0	1	1	0	0	1	0	1	
310		.675	0	1	1	0	1	1	0	0	1	0	1	
311		.6875	1	1	1	0	1	1	0	0	1	0	1	
312		163.700	0	0	0	1	1	1	0	0	1	0	1	
313		.7125	1	0	0	1	1	1	0	0	1	0	1	
314		.725	0	1	0	1	1	1	0	0	1	0	1	
315		.7375	1	1	0	1	1	1	0	0	1	0	1	
316		.750	0	0	1	1	1	1	0	0	1	0	1	
317		.7625	1	0	1	1	1	1	0	0	1	0	1	
318		.775	0	1	1	1	1	1	0	0	1	0	1	
HL 319		.7875	1	1	1	1	1	1	0	0	1	0	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	N11	NOTE
HL 320		163.800	0	0	0	0	0	0	1	0	1	0	1	
321		.8125	1	0	0	0	0	0	1	0	1	0	1	
322		.825	0	1	0	0	0	0	1	0	1	0	1	
323		.8375	1	1	0	0	0	0	1	0	1	0	1	
324		.850	0	0	1	0	0	0	1	0	1	0	1	
325		.8625	1	0	1	0	0	0	1	0	1	0	1	
326		.875	0	1	1	0	0	0	1	0	1	0	1	
327		.8875	1	1	1	0	0	0	1	0	1	0	1	
328		163.900	0	0	0	1	0	0	1	0	1	0	1	
329		.9125	1	0	0	1	0	0	1	0	1	0	1	
330		.925	0	1	0	1	0	0	1	0	1	0	1	
331		.9375	1	1	0	1	0	0	1	0	1	0	1	
332		.950	0	0	1	1	0	0	1	0	1	0	1	
333		.9625	1	0	1	1	0	0	1	0	1	0	1	
334		.975	0	1	1	1	0	0	1	0	1	0	1	
335		.9875	1	1	1	1	0	0	1	0	1	0	1	
336		164.000	0	0	0	0	1	0	1	0	1	0	1	
337		.0125	1	0	0	0	1	0	1	0	1	0	1	
338		.025	0	1	0	0	1	0	1	0	1	0	1	
339		.0375	1	1	0	0	1	0	1	0	1	0	1	
340		.050	0	0	1	0	1	0	1	0	1	0	1	
341		.0625	1	0	1	0	1	0	1	0	1	0	1	
342		.075	0	1	1	0	1	0	1	0	1	0	1	
343		.0875	1	1	1	0	1	0	1	0	1	0	1	
344		164.100	0	0	0	1	1	0	1	0	1	0	1	
345		.1125	1	0	0	1	1	0	1	0	1	0	1	
346		.125	0	1	0	1	1	0	1	0	1	0	1	
347		.1375	1	1	0	1	1	0	1	0	1	0	1	
348		.150	0	0	1	1	1	0	1	0	1	0	1	
349		.1625	1	0	1	1	1	0	1	0	1	0	1	
350		.175	0	1	1	1	1	0	1	0	1	0	1	
351		.1875	1	1	1	1	1	0	1	0	1	0	1	
352		164.200	0	0	0	0	0	1	1	0	1	0	1	
353		.2125	1	0	0	0	0	1	1	0	1	0	1	
354		.225	0	1	0	0	0	1	1	0	1	0	1	
355		.2375	1	1	0	0	0	1	1	0	1	0	1	
356		.250	0	0	1	0	0	1	1	0	1	0	1	
357		.2625	1	0	1	0	0	1	1	0	1	0	1	
358		.275	0	1	1	0	0	1	1	0	1	0	1	
359		.2875	1	1	1	0	0	1	1	0	1	0	1	
360		164.300	0	0	0	1	0	1	1	0	1	0	1	
361		.3125	1	0	0	1	0	1	1	0	1	0	1	
362		.325	0	1	0	1	0	1	1	0	1	0	1	
363		.3375	1	1	0	1	0	1	1	0	1	0	1	
364		.350	0	0	1	1	0	1	1	0	1	0	1	
365		.3625	1	0	1	1	0	1	1	0	1	0	1	
366		.375	0	1	1	1	0	1	1	0	1	0	1	
367		.3875	1	1	1	1	0	1	1	0	1	0	1	
368		164.400	0	0	0	0	1	1	1	0	1	0	1	
369		.4125	1	0	0	0	1	1	1	0	1	0	1	
370		.425	0	1	0	0	1	1	1	0	1	0	1	
371		.4375	1	1	0	0	1	1	1	0	1	0	1	
372		.450	0	0	1	0	1	1	1	0	1	0	1	
373		.4625	1	0	1	0	1	1	1	0	1	0	1	
374		.475	0	1	1	0	1	1	1	0	1	0	1	
375		.4875	1	1	1	0	1	1	1	0	1	0	1	
376		164.500	0	0	0	1	1	1	1	0	1	0	1	
377		.5125	1	0	0	1	1	1	1	0	1	0	1	
378		.525	0	1	0	1	1	1	1	0	1	0	1	
379		.5375	1	1	0	1	1	1	1	0	1	0	1	
380		.550	0	0	1	1	1	1	1	0	1	0	1	
381		.5625	1	0	1	1	1	1	1	0	1	0	1	
382		.575	0	1	1		1	1	1		1	0	1	
HL 383		.5875	1	1	1		1	1	1		1	0	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	F/L	NOTE
HL 384		164. 600	0	0	0	0	0	0	0	1	1	0	1	
385		. 6125	1	0	0	0	0	0	0	1	1	0	1	
386		. 625	0	1	0	0	0	0	0	1	1	0	1	
387		. 6375	1	1	0	0	0	0	0	1	1	0	1	
388		. 650	0	0	1	0	0	0	0	1	1	0	1	
389		. 6625	1	0	1	0	0	0	0	1	1	0	1	
390		. 675	0	1	1	0	0	0	0	1	1	0	1	
391		. 6875	1	1	1	0	0	0	0	1	1	0	1	
392		164. 700	0	0	0	1	0	0	0	1	1	0	1	
393		. 7125	1	0	0	1	0	0	0	1	1	0	1	
394		. 725	0	1	0	1	0	0	0	1	1	0	1	
395		. 7375	1	1	0	1	0	0	0	1	1	0	1	
396		. 750	0	0	1	1	0	0	0	1	1	0	1	
397		. 7625	1	0	1	1	0	0	0	1	1	0	1	
398		. 775	0	1	1	1	0	0	0	1	1	0	1	
399		. 7875	1	1	1	1	0	0	0	1	1	0	1	
400		164. 800	0	0	0	0	1	0	0	1	1	0	1	
401		. 8125	1	0	0	0	1	0	0	1	1	0	1	
402		. 825	0	1	0	0	1	0	0	1	1	0	1	
403		. 8375	1	1	0	0	1	0	0	1	1	0	1	
404		. 850	0	0	1	0	1	0	0	1	1	0	1	
405		. 8625	1	0	1	0	1	0	0	1	1	0	1	
406		. 875	0	1	1	0	1	0	0	1	1	0	1	
407		. 8875	1	1	1	0	1	0	0	1	1	0	1	
408		164. 900	0	0	0	1	1	0	0	1	1	0	1	
409		. 9125	1	0	0	1	1	0	0	1	1	0	1	
410		. 925	0	1	0	1	1	0	0	1	1	0	1	
411		. 9375	1	1	0	1	1	0	0	1	1	0	1	
412		. 950	0	0	1	1	1	0	0	1	1	0	1	
413		. 9625	1	0	1	1	1	0	0	1	1	0	1	
414		. 975	0	1	1	1	1	0	0	1	1	0	1	
415		. 9875	1	1	1	1	1	0	0	1	1	0	1	
416		165. 000	0	0	0	0	0	1	0	1	1	0	1	
417		. 0125	1	0	0	0	0	1	0	1	1	0	1	
418		. 025	0	1	0	0	0	1	0	1	1	0	1	
419		. 0375	1	1	0	0	0	1	0	1	1	0	1	
420		. 050	0	0	1	0	0	1	0	1	1	0	1	
421		. 0625	1	0	1	0	0	1	0	1	1	0	1	
422		. 075	0	1	1	0	0	1	0	1	1	0	1	
423		. 0875	1	1	1	0	0	1	0	1	1	0	1	
424		165. 100	0	0	0	1	0	1	0	1	1	0	1	
425		. 1125	1	0	0	1	0	1	0	1	1	0	1	
426		. 125	0	1	0	1	0	1	0	1	1	0	1	
427		. 1375	1	1	0	1	0	1	0	1	1	0	1	
428		. 150	0	0	1	1	0	1	0	1	1	0	1	
429		. 1625	1	0	1	1	0	1	0	1	1	0	1	
430		. 175	0	1	1	1	0	1	0	1	1	0	1	
431		. 1875	1	1	1	1	0	1	0	1	1	0	1	
432		165. 200	0	0	0	0	1	1	0	1	1	0	1	
433		. 2125	1	0	0	0	1	1	0	1	1	0	1	
434		. 225	0	1	0	0	1	1	0	1	1	0	1	
435		. 2375	1	1	0	0	1	1	0	1	1	0	1	
436		. 250	0	0	1	0	1	1	0	1	1	0	1	
437		. 2625	1	0	1	0	1	1	0	1	1	0	1	
438		. 275	0	1	1	0	1	1	0	1	1	0	1	
439		. 2875	1	1	1	0	1	1	0	1	1	0	1	
440		165. 300	0	0	0	1	1	1	0	1	1	0	1	
441		. 3125	1	0	0	1	1	1	0	1	1	0	1	
442		. 325	0	1	0	1	1	1	0	1	1	0	1	
443		. 3375	1	1	0	1	1	1	0	1	1	0	1	
444		. 350	0	0	1	1	1	1	0	1	1	0	1	
445		. 3625	1	0	1	1	1	1	0	1	1	0	1	
446		. 375	0	1	1	1	1	1	0	1	1	0	1	
HL 447		. 3875	1	1	1	1	1	1	0	1	1	0	1	

TABLE CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	N11	NOTE
HL 448		165.400	0	0	0	0	0	0	1	1	1	0	1	
449		.4125	1	0	0	0	0	0	1	1	1	0	1	
450		.425	0	1	0	0	0	0	1	1	1	0	1	
451		.4375	1	1	0	0	0	0	1	1	1	0	1	
452		.450	0	0	1	0	0	0	1	1	1	0	1	
453		.4625	1	0	1	0	0	0	1	1	1	0	1	
454		.475	0	1	1	0	0	0	1	1	1	0	1	
455		.4875	1	1	1	0	0	0	1	1	1	0	1	
456		165.500	0	0	0	1	0	0	1	1	1	0	1	
457		.5125	1	0	0	1	0	0	1	1	1	0	1	
458		.525	0	1	0	1	0	0	1	1	1	0	1	
459		.5375	1	1	0	1	0	0	1	1	1	0	1	
460		.550	0	0	1	1	0	0	1	1	1	0	1	
461		.5625	1	0	1	1	0	0	1	1	1	0	1	
462		.575	0	1	1	1	0	0	1	1	1	0	1	
463		.5875	1	1	1	1	0	0	1	1	1	0	1	
464		165.600	0	0	0	0	1	0	1	1	1	0	1	
465		.6125	1	0	0	0	1	0	1	1	1	0	1	
466		.625	0	1	0	0	1	0	1	1	1	0	1	
467		.6375	1	1	0	0	1	0	1	1	1	0	1	
468		.650	0	0	1	0	1	0	1	1	1	0	1	
469		.6625	1	0	1	0	1	0	1	1	1	0	1	
470		.675	0	1	1	0	1	0	1	1	1	0	1	
471		.6875	1	1	1	0	1	0	1	1	1	0	1	
472		165.700	0	0	0	1	1	0	1	1	1	0	1	
473		.7125	1	0	0	1	1	0	1	1	1	0	1	
474		.725	0	1	0	1	1	0	1	1	1	0	1	
475		.7375	1	1	0	1	1	0	1	1	1	0	1	
476		.750	0	0	1	1	1	0	1	1	1	0	1	
477		.7625	1	0	1	1	1	0	1	1	1	0	1	
478		.775	0	1	1	1	1	0	1	1	1	0	1	
479		.7875	1	1	1	1	1	0	1	1	1	0	1	
480		165.800	0	0	0	0	0	1	1	1	1	0	1	
481		.8125	1	0	0	0	0	1	1	1	1	0	1	
482		.825	0	1	0	0	0	1	1	1	1	0	1	
483		.8375	1	1	0	0	0	1	1	1	1	0	1	
484		.850	0	0	1	0	0	1	1	1	1	0	1	
485		.8625	1	0	1	0	0	1	1	1	1	0	1	
486		.875	0	1	1	0	0	1	1	1	1	0	1	
487		.8875	1	1	1	0	0	1	1	1	1	0	1	
488		165.900	0	0	0	1	0	1	1	1	1	0	1	
489		.9125	1	0	0	1	0	1	1	1	1	0	1	
490		.925	0	1	0	1	0	1	1	1	1	0	1	
491		.9375	1	1	0	1	0	1	1	1	1	0	1	
492		.950	0	0	1	1	0	1	1	1	1	0	1	
493		.9625	1	0	1	1	0	1	1	1	1	0	1	
494		.975	0	1	1	1	0	1	1	1	1	0	1	
495		.9875	1	1	1	1	0	1	1	1	1	0	1	
496		166.000	0	0	0	0	1	1	1	1	1	0	1	
497		.0125	1	0	0	0	1	1	1	1	1	0	1	
498		.025	0	1	0	0	1	1	1	1	1	0	1	
499		.0375	1	1	0	0	1	1	1	1	1	0	1	
500		.050	0	0	1	0	1	1	1	1	1	0	1	
501		.0625	1	0	1	0	1	1	1	1	1	0	1	
502		.075	0	1	1	0	1	1	1	1	1	0	1	
503		.0875	1	1	1	0	1	1	1	1	1	0	1	
504		166.100	0	0	0	1	1	1	1	1	1	0	1	
505		.1125	1	0	0	1	1	1	1	1	1	0	1	
506		.125	0	1	0	1	1	1	1	1	1	0	1	
507		.1375	1	1	0	1	1	1	1	1	1	0	1	
508		.150	0	0	1	1	1	1	1	1	1	0	1	
509		.1625	1	0	1	1	1	1	1	1	1	0	1	
510		.175	0	1	1		1	1	1		1	0	1	
HL 511		.1875	1	1	1		1	1	1		1	0	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H. L. N11	NOTE
HH 0			0	0	0	0	0	0	0	0	0	1	1	
1			1	0	0	0	0	0	0	0	0	1	1	
2			0	1	0	0	0	0	0	0	0	1	1	
3			1	1	0	0	0	0	0	0	0	1	1	
4			0	0	1	0	0	0	0	0	0	1	1	
5			1	0	1	0	0	0	0	0	0	1	1	
6			0	1	1	0	0	0	0	0	0	1	1	
7			1	1	1	0	0	0	0	0	0	1	1	
8			0	0	0	1	0	0	0	0	0	1	1	
9			1	0	0	1	0	0	0	0	0	1	1	
10			0	1	0	1	0	0	0	0	0	1	1	
11			1	1	0	1	0	0	0	0	0	1	1	
12			0	0	1	1	0	0	0	0	0	1	1	
13			1	0	1	1	0	0	0	0	0	1	1	
14			0	1	1	1	0	0	0	0	0	1	1	
15			1	1	1	1	0	0	0	0	0	1	1	
16			0	0	0	0	1	0	0	0	0	1	1	
17			1	0	0	0	1	0	0	0	0	1	1	
18			0	1	0	0	1	0	0	0	0	1	1	
19			1	1	0	0	1	0	0	0	0	1	1	
20			0	0	1	0	1	0	0	0	0	1	1	
21			1	0	1	0	1	0	0	0	0	1	1	
22			0	1	1	0	1	0	0	0	0	1	1	
23			1	1	1	0	1	0	0	0	0	1	1	
24			0	0	0	1	1	0	0	0	0	1	1	
25			1	0	0	1	1	0	0	0	0	1	1	
26			0	1	0	1	1	0	0	0	0	1	1	
27			1	1	0	1	1	0	0	0	0	1	1	
28			0	0	1	1	1	0	0	0	0	1	1	
29			1	0	1	1	1	0	0	0	0	1	1	
30			0	1	1	1	1	0	0	0	0	1	1	
31		166. 1875	1	1	1	1	1	0	0	0	0	1	1	
32		166. 200	0	0	0	0	0	1	0	0	0	1	1	
33		. 2125	1	0	0	0	0	1	0	0	0	1	1	
34		. 225	0	1	0	0	0	1	0	0	0	1	1	
35		. 2375	1	1	0	0	0	1	0	0	0	1	1	
36		. 250	0	0	1	0	0	1	0	0	0	1	1	
37		. 2625	1	0	1	0	0	1	0	0	0	1	1	
38		. 275	0	1	1	0	0	1	0	0	0	1	1	
39		. 2875	1	1	1	0	0	1	0	0	0	1	1	
40		166. 300	0	0	0	1	0	1	0	0	0	1	1	
41		. 3125	1	0	0	1	0	1	0	0	0	1	1	
42		. 325	0	1	0	1	0	1	0	0	0	1	1	
43		. 3375	1	1	0	1	0	1	0	0	0	1	1	
44		. 350	0	0	1	1	0	1	0	0	0	1	1	
45		. 3625	1	0	1	1	0	1	0	0	0	1	1	
46		. 375	0	1	1	1	0	1	0	0	0	1	1	
47		. 3875	1	1	1	1	0	1	0	0	0	1	1	
48		166. 400	0	0	0	0	1	1	0	0	0	1	1	
49		. 4125	1	0	0	0	1	1	0	0	0	1	1	
50		. 425	0	1	0	0	1	1	0	0	0	1	1	
51		. 4375	1	1	0	0	1	1	0	0	0	1	1	
52		. 450	0	0	1	0	1	1	0	0	0	1	1	
53		. 4625	1	0	1	0	1	1	0	0	0	1	1	
54		. 475	0	1	1	0	1	1	0	0	0	1	1	
55		. 4875	1	1	1	0	1	1	0	0	0	1	1	
56		166. 500	0	0	0	1	1	1	0	0	0	1	1	
57		. 5125	1	0	0	1	1	1	0	0	0	1	1	
58		. 525	0	1	0	1	1	1	0	0	0	1	1	
59		. 5375	1	1	0	1	1	1	0	0	0	1	1	
60		. 550	0	0	1	1	1	1	0	0	0	1	1	
61		. 5625	1	0	1	1	1	1	0	0	0	1	1	
62		. 575	0	1	1	1	1	1	0	0	0	1	1	
HH 63		. 5875	1	1	1	1	1	1	0	0	0	1	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HH 64		166. 600	0	0	0	0	0	0	1	0	0	1	1	
65		. 6125	1	0	0	0	0	0	1	0	0	1	1	
66		. 625	0	1	0	0	0	0	1	0	0	1	1	
67		. 6375	1	1	0	0	0	0	1	0	0	1	1	
68		. 650	0	0	1	0	0	0	1	0	0	1	1	
69		. 6625	1	0	1	0	0	0	1	0	0	1	1	
70		. 675	0	1	1	0	0	0	1	0	0	1	1	
71		. 6875	1	1	1	0	0	0	1	0	0	1	1	
72		166. 700	0	0	0	1	0	0	1	0	0	1	1	
73		. 7125	1	0	0	1	0	0	1	0	0	1	1	
74		. 725	0	1	0	1	0	0	1	0	0	1	1	
75		. 7375	1	1	0	1	0	0	1	0	0	1	1	
76		. 750	0	0	1	1	0	0	1	0	0	1	1	
77		. 7625	1	0	1	1	0	0	1	0	0	1	1	
78		. 775	0	1	1	1	0	0	1	0	0	1	1	
79		. 7875	1	1	1	1	0	0	1	0	0	1	1	
80		166. 800	0	0	0	0	1	0	1	0	0	1	1	
81		. 8125	1	0	0	0	1	0	1	0	0	1	1	
82		. 825	0	1	0	0	1	0	1	0	0	1	1	
83		. 8375	1	1	0	0	1	0	1	0	0	1	1	
84		. 850	0	0	1	0	1	0	1	0	0	1	1	
85		. 8625	1	0	1	0	1	0	1	0	0	1	1	
86		. 875	0	1	1	0	1	0	1	0	0	1	1	
87		. 8875	1	1	1	0	1	0	1	0	0	1	1	
88		166. 900	0	0	0	1	1	0	1	0	0	1	1	
89		. 9125	1	0	0	1	1	0	1	0	0	1	1	
90		. 925	0	1	0	1	1	0	1	0	0	1	1	
91		. 9375	1	1	0	1	1	0	1	0	0	1	1	
92		. 950	0	0	1	1	1	0	1	0	0	1	1	
93		. 9625	1	0	1	1	1	0	1	0	0	1	1	
94		. 975	0	1	1	1	1	0	1	0	0	1	1	
95		. 9875	1	1	1	1	1	0	1	0	0	1	1	
96		167. 000	0	0	0	0	0	1	1	0	0	1	1	
97		. 0125	1	0	0	0	0	1	1	0	0	1	1	
98		. 025	0	1	0	0	0	1	1	0	0	1	1	
99		. 0375	1	1	0	0	0	1	1	0	0	1	1	
100		. 050	0	0	1	0	0	1	1	0	0	1	1	
101		. 0625	1	0	1	0	0	1	1	0	0	1	1	
102		. 075	0	1	1	0	0	1	1	0	0	1	1	
103		. 0875	1	1	1	0	0	1	1	0	0	1	1	
104		167. 100	0	0	0	1	0	1	1	0	0	1	1	
105		. 1125	1	0	0	1	0	1	1	0	0	1	1	
106		. 125	0	1	0	1	0	1	1	0	0	1	1	
107		. 1375	1	1	0	1	0	1	1	0	0	1	1	
108		. 150	0	0	1	1	0	1	1	0	0	1	1	
109		. 1625	1	0	1	1	0	1	1	0	0	1	1	
110		. 175	0	1	1	1	0	1	1	0	0	1	1	
111		. 1875	1	1	1	1	0	1	1	0	0	1	1	
112		167. 200	0	0	0	0	1	1	1	0	0	1	1	
113		. 2125	1	0	0	0	1	1	1	0	0	1	1	
114		. 225	0	1	0	0	1	1	1	0	0	1	1	
115		. 2375	1	1	0	0	1	1	1	0	0	1	1	
116		. 250	0	0	1	0	1	1	1	0	0	1	1	
117		. 2625	1	0	1	0	1	1	1	0	0	1	1	
118		. 275	0	1	1	0	1	1	1	0	0	1	1	
119		. 2875	1	1	1	0	1	1	1	0	0	1	1	
120		167. 300	0	0	0	1	1	1	1	0	0	1	1	
121		. 3125	1	0	0	1	1	1	1	0	0	1	1	
122		. 325	0	1	0	1	1	1	1	0	0	1	1	
123		. 3375	1	1	0	1	1	1	1	0	0	1	1	
124		. 350	0	0	1	1	1	1	1	0	0	1	1	
125		. 3625	1	0	1	1	1	1	1	0	0	1	1	
126		. 375	0	1	1		1	1	1		0	1	1	
HH 127		. 3875	1	1	1		1	1	1		0	1	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HH 128		167.400	0	0	0	0	0	0	0	1	0	1	1	
129		.4125	1	0	0	0	0	0	0	1	0	1	1	
130		.425	0	1	0	0	0	0	0	1	0	1	1	
131		.4375	1	1	0	0	0	0	0	1	0	1	1	
132		.450	0	0	1	0	0	0	0	1	0	1	1	
133		.4625	1	0	1	0	0	0	0	1	0	1	1	
134		.475	0	1	1	0	0	0	0	1	0	1	1	
135		.4875	1	1	1	0	0	0	0	1	0	1	1	
136		167.500	0	0	0	1	0	0	0	1	0	1	1	
137		.5125	1	0	0	1	0	0	0	1	0	1	1	
138		.525	0	1	0	1	0	0	0	1	0	1	1	
139		.5375	1	1	0	1	0	0	0	1	0	1	1	
140		.550	0	0	1	1	0	0	0	1	0	1	1	
141		.5625	1	0	1	1	0	0	0	1	0	1	1	
142		.575	0	1	1	1	0	0	0	1	0	1	1	
143		.5875	1	1	1	1	0	0	0	1	0	1	1	
144		167.600	0	0	0	0	1	0	0	1	0	1	1	
145		.6125	1	0	0	0	1	0	0	1	0	1	1	
146		.625	0	1	0	0	1	0	0	1	0	1	1	
147		.6375	1	1	0	0	1	0	0	1	0	1	1	
148		.650	0	0	1	0	1	0	0	1	0	1	1	
149		.6625	1	0	1	0	1	0	0	1	0	1	1	
150		.675	0	1	1	0	1	0	0	1	0	1	1	
151		.6875	1	1	1	0	1	0	0	1	0	1	1	
152		167.700	0	0	0	1	1	0	0	1	0	1	1	
153		.7125	1	0	0	1	1	0	0	1	0	1	1	
154		.725	0	1	0	1	1	0	0	1	0	1	1	
155		.7375	1	1	0	1	1	0	0	1	0	1	1	
156		.750	0	0	1	1	1	0	0	1	0	1	1	
157		.7625	1	0	1	1	1	0	0	1	0	1	1	
158*		.775	0	1	1	1	1	0	0	1	0	1	1	
159		.7875	1	1	1	1	1	0	0	1	0	1	1	
160		167.800	0	0	0	0	0	1	0	1	0	1	1	
161		.8125	1	0	0	0	0	1	0	1	0	1	1	
162		.825	0	1	0	0	0	1	0	1	0	1	1	
163		.8375	1	1	0	0	0	1	0	1	0	1	1	
164		.850	0	0	1	0	0	1	0	1	0	1	1	
165		.8625	1	0	1	0	0	1	0	1	0	1	1	
166		.875	0	1	1	0	0	1	0	1	0	1	1	
167		.8875	1	1	1	0	0	1	0	1	0	1	1	
168		167.900	0	0	0	1	0	1	0	1	0	1	1	
169		.9125	1	0	0	1	0	1	0	1	0	1	1	
170		.925	0	1	0	1	0	1	0	1	0	1	1	
171		.9375	1	1	0	1	0	1	0	1	0	1	1	
172		.950	0	0	1	1	0	1	0	1	0	1	1	
173		.9625	1	0	1	1	0	1	0	1	0	1	1	
174		.975	0	1	1	1	0	1	0	1	0	1	1	
175		.9875	1	1	1	1	0	1	0	1	0	1	1	
176		168.000	0	0	0	0	1	1	0	1	0	1	1	
177		.0125	1	0	0	0	1	1	0	1	0	1	1	
178		.025	0	1	0	0	1	1	0	1	0	1	1	
179		.0375	1	1	0	0	1	1	0	1	0	1	1	
180		.050	0	0	1	0	1	1	0	1	0	1	1	
181		.0625	1	0	1	0	1	1	0	1	0	1	1	
182		.075	0	1	1	0	1	1	0	1	0	1	1	
183		.0875	1	1	1	0	1	1	0	1	0	1	1	
184		168.100	0	0	0	1	1	1	0	1	0	1	1	
185		.1125	1	0	0	1	1	1	0	1	0	1	1	
186		.125	0	1	0	1	1	1	0	1	0	1	1	
187		.1375	1	1	0	1	1	1	0	1	0	1	1	
188		.150	0	0	1	1	1	1	0	1	0	1	1	
189		.1625	1	0	1	1	1	1	0	1	0	1	1	
190		.175	0	1	1	1	1	1	0	1	0	1	1	
HH 191		.1875	1	1	1	1	1	1	0	1	0	1	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HH 192		168.200	0	0	0	0	0	0	1	1	0	1	1	
193		.2125	1	0	0	0	0	0	1	1	0	1	1	
194		.225	0	1	0	0	0	0	1	1	0	1	1	
195		.2375	1	1	0	0	0	0	1	1	0	1	1	
196		.250	0	0	1	0	0	0	1	1	0	1	1	
197		.2625	1	0	1	0	0	0	1	1	0	1	1	
198		.275	0	1	1	0	0	0	1	1	0	1	1	
199		.2875	1	1	1	0	0	0	1	1	0	1	1	
200		168.300	0	0	0	1	0	0	1	1	0	1	1	
201		.3125	1	0	0	1	0	0	1	1	0	1	1	
202		.325	0	1	0	1	0	0	1	1	0	1	1	
203		.3375	1	1	0	1	0	0	1	1	0	1	1	
204		.350	0	0	1	1	0	0	1	1	0	1	1	
205		.3625	1	0	1	1	0	0	1	1	0	1	1	
206		.375	0	1	1	1	0	0	1	1	0	1	1	
207		.3875	1	1	1	1	0	0	1	1	0	1	1	
208		168.400	0	0	0	0	1	0	1	1	0	1	1	
209		.4125	1	0	0	0	1	0	1	1	0	1	1	
210		.425	0	1	0	0	1	0	1	1	0	1	1	
211		.4375	1	1	0	0	1	0	1	1	0	1	1	
212		.450	0	0	1	0	1	0	1	1	0	1	1	
213		.4625	1	0	1	0	1	0	1	1	0	1	1	
214		.475	0	1	1	0	1	0	1	1	0	1	1	
215		.4875	1	1	1	0	1	0	1	1	0	1	1	
216		168.500	0	0	0	1	1	0	1	1	0	1	1	
217		.5125	1	0	0	1	1	0	1	1	0	1	1	
218		.525	0	1	0	1	1	0	1	1	0	1	1	
219		.5375	1	1	0	1	1	0	1	1	0	1	1	
220		.550	0	0	1	1	1	0	1	1	0	1	1	
221		.5625	1	0	1	1	1	0	1	1	0	1	1	
222		.575	0	1	1	1	1	0	1	1	0	1	1	
223		.5875	1	1	1	1	1	0	1	1	0	1	1	
224		168.600	0	0	0	0	0	1	1	1	0	1	1	
225		.6125	1	0	0	0	0	1	1	1	0	1	1	
226		.625	0	1	0	0	0	1	1	1	0	1	1	
227		.6375	1	1	0	0	0	1	1	1	0	1	1	
228		.650	0	0	1	0	0	1	1	1	0	1	1	
229		.6625	1	0	1	0	0	1	1	1	0	1	1	
230		.675	0	1	1	0	0	1	1	1	0	1	1	
231		.6875	1	1	1	0	0	1	1	1	0	1	1	
232		168.700	0	0	0	1	0	1	1	1	0	1	1	
233		.7125	1	0	0	1	0	1	1	1	0	1	1	
234		.725	0	1	0	1	0	1	1	1	0	1	1	
235		.7375	1	1	0	1	0	1	1	1	0	1	1	
236		.750	0	0	1	1	0	1	1	1	0	1	1	
237		.7625	1	0	1	1	0	1	1	1	0	1	1	
238		.775	0	1	1	1	0	1	1	1	0	1	1	
239		.7875	1	1	1	1	0	1	1	1	0	1	1	
240		168.800	0	0	0	0	1	1	1	1	0	1	1	
241		.8125	1	0	0	0	1	1	1	1	0	1	1	
242		.825	0	1	0	0	1	1	1	1	0	1	1	
243		.8375	1	1	0	0	1	1	1	1	0	1	1	
244		.850	0	0	1	0	1	1	1	1	0	1	1	
245		.8625	1	0	1	0	1	1	1	1	0	1	1	
246		.875	0	1	1	0	1	1	1	1	0	1	1	
247		.8875	1	1	1	0	1	1	1	1	0	1	1	
248		168.900	0	0	0	1	1	1	1	1	0	1	1	
249		.9125	1	0	0	1	1	1	1	1	0	1	1	
250		.925	0	1	0	1	1	1	1	1	0	1	1	
251		.9375	1	1	0	1	1	1	1	1	0	1	1	
252		.950	0	0	1	1	1	1	1	1	0	1	1	
253		.9625	1	0	1	1	1	1	1	1	0	1	1	
254		.975	0	1	1		1	1	1	1		1	1	
HH 255		.9875	1	1	1	1	1	1	1	1	0	1	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H.L. N11	NOTE
HH 256		169.000	0	0	0	0	0	0	0	0	1	1	1	
257		.0125	1	0	0	0	0	0	0	0	1	1	1	
258		.025	0	1	0	0	0	0	0	0	1	1	1	
259		.0375	1	1	0	0	0	0	0	0	1	1	1	
260		.050	0	0	1	0	0	0	0	0	1	1	1	
261		.0625	1	0	1	0	0	0	0	0	1	1	1	
262		.075	0	1	1	0	0	0	0	0	1	1	1	
263		.0875	1	1	1	0	0	0	0	0	1	1	1	
264		169.100	0	0	0	1	0	0	0	0	1	1	1	
265		.1125	1	0	0	1	0	0	0	0	1	1	1	
266		.125	0	1	0	1	0	0	0	0	1	1	1	
267		.1375	1	1	0	1	0	0	0	0	1	1	1	
268		.150	0	0	1	1	0	0	0	0	1	1	1	
269		.1625	1	0	1	1	0	0	0	0	1	1	1	
270		.175	0	1	1	1	0	0	0	0	1	1	1	
271		.1875	1	1	1	1	0	0	0	0	1	1	1	
272		169.200	0	0	0	0	1	0	0	0	1	1	1	
273		.2125	1	0	0	0	1	0	0	0	1	1	1	
274		.225	0	1	0	0	1	0	0	0	1	1	1	
275		.2375	1	1	0	0	1	0	0	0	1	1	1	
276		.250	0	0	1	0	1	0	0	0	1	1	1	
277		.2625	1	0	1	0	1	0	0	0	1	1	1	
278		.275	0	1	1	0	1	0	0	0	1	1	1	
279		.2875	1	1	1	0	1	0	0	0	1	1	1	
280		169.300	0	0	0	1	1	0	0	0	1	1	1	
281		.3125	1	0	0	1	1	0	0	0	1	1	1	
282		.325	0	1	0	1	1	0	0	0	1	1	1	
283		.3375	1	1	0	1	1	0	0	0	1	1	1	
284		.350	0	0	1	1	1	0	0	0	1	1	1	
285		.3625	1	0	1	1	1	0	0	0	1	1	1	
286		.375	0	1	1	1	1	0	0	0	1	1	1	
287		.3875	1	1	1	1	1	0	0	0	1	1	1	
288		169.400	0	0	0	0	0	1	0	0	1	1	1	
289		.4125	1	0	0	0	0	1	0	0	1	1	1	
290		.425	0	1	0	0	0	1	0	0	1	1	1	
291		.4375	1	1	0	0	0	1	0	0	1	1	1	
292		.450	0	0	1	0	0	1	0	0	1	1	1	
293		.4625	1	0	1	0	0	1	0	0	1	1	1	
294		.475	0	1	1	0	0	1	0	0	1	1	1	
295		.4875	1	1	1	0	0	1	0	0	1	1	1	
296		169.500	0	0	0	1	0	1	0	0	1	1	1	
297		.5125	1	0	0	1	0	1	0	0	1	1	1	
298		.525	0	1	0	1	0	1	0	0	1	1	1	
299		.5375	1	1	0	1	0	1	0	0	1	1	1	
300		.550	0	0	1	1	0	1	0	0	1	1	1	
301		.5625	1	0	1	1	0	1	0	0	1	1	1	
302		.575	0	1	1	1	0	1	0	0	1	1	1	
303		.5875	1	1	1	1	0	1	0	0	1	1	1	
304		169.600	0	0	0	0	1	1	0	0	1	1	1	
305		.6125	1	0	0	0	1	1	0	0	1	1	1	
306		.625	0	1	0	0	1	1	0	0	1	1	1	
307		.6375	1	1	0	0	1	1	0	0	1	1	1	
308		.650	0	0	1	0	1	1	0	0	1	1	1	
309		.6625	1	0	1	0	1	1	0	0	1	1	1	
310		.675	0	1	1	0	1	1	0	0	1	1	1	
311		.6875	1	1	1	0	1	1	0	0	1	1	1	
312		169.700	0	0	0	1	1	1	0	0	1	1	1	
313		.7125	1	0	0	1	1	1	0	0	1	1	1	
314		.725	0	1	0	1	1	1	0	0	1	1	1	
315		.7375	1	1	0	1	1	1	0	0	1	1	1	
316		.750	0	0	1	1	1	1	0	0	1	1	1	
317		.7625	1	0	1	1	1	1	0	0	1	1	1	
318		.775	0	1	1	1	1	1	0	0	1	1	1	
HH 319		.7875	1	1	1	1	1	1	0	0	1	1	1	

CHANNEL CODE NO	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HH 320		169.800	0	0	0	0	0	0	1	0	1	1	1	
321		.8125	1	0	0	0	0	0	1	0	1	1	1	
322		.825	0	1	0	0	0	0	1	0	1	1	1	
323		.8375	1	1	0	0	0	0	1	0	1	1	1	
324		.850	0	0	1	0	0	0	1	0	1	1	1	
325		.8625	1	0	1	0	0	0	1	0	1	1	1	
326		.875	0	1	1	0	0	0	1	0	1	1	1	
327		.8875	1	1	1	0	0	0	1	0	1	1	1	
328		169.900	0	0	0	1	0	0	1	0	1	1	1	
329		.9125	1	0	0	1	0	0	1	0	1	1	1	
330		.925	0	1	0	1	0	0	1	0	1	1	1	
331		.9375	1	1	0	1	0	0	1	0	1	1	1	
332		.950	0	0	1	1	0	0	1	0	1	1	1	
333		.9625	1	0	1	1	0	0	1	0	1	1	1	
334		.975	0	1	1	1	0	0	1	0	1	1	1	
335		.9875	1	1	1	1	0	0	1	0	1	1	1	
336		170.000	0	0	0	0	1	0	1	0	1	1	1	
337		.0125	1	0	0	0	1	0	1	0	1	1	1	
338		.025	0	1	0	0	1	0	1	0	1	1	1	
339		.0375	1	1	0	0	1	0	1	0	1	1	1	
340		.050	0	0	1	0	1	0	1	0	1	1	1	
341		.0625	1	0	1	0	1	0	1	0	1	1	1	
342		.075	0	1	1	0	1	0	1	0	1	1	1	
343		.0875	1	1	1	0	1	0	1	0	1	1	1	
344		170.100	0	0	0	1	1	0	1	0	1	1	1	
345		.1125	1	0	0	1	1	0	1	0	1	1	1	
346		.125	0	1	0	1	1	0	1	0	1	1	1	
347		.1375	1	1	0	1	1	0	1	0	1	1	1	
348		.150	0	0	1	1	1	0	1	0	1	1	1	
349		.1625	1	0	1	1	1	0	1	0	1	1	1	
350		.175	0	1	1	1	1	0	1	0	1	1	1	
351		.1875	1	1	1	1	1	0	1	0	1	1	1	
352		170.200	0	0	0	0	0	1	1	0	1	1	1	
353		.2125	1	0	0	0	0	1	1	0	1	1	1	
354		.225	0	1	0	0	0	1	1	0	1	1	1	
355		.2375	1	1	0	0	0	1	1	0	1	1	1	
356		.250	0	0	1	0	0	1	1	0	1	1	1	
357		.2625	1	0	1	0	0	1	1	0	1	1	1	
358		.275	0	1	1	0	0	1	1	0	1	1	1	
359		.2875	1	1	1	0	0	1	1	0	1	1	1	
360		170.300	0	0	0	1	0	1	1	0	1	1	1	
361		.3125	1	0	0	1	0	1	1	0	1	1	1	
362		.325	0	1	0	1	0	1	1	0	1	1	1	
363		.3375	1	1	0	1	0	1	1	0	1	1	1	
364		.350	0	0	1	1	0	1	1	0	1	1	1	
365		.3625	1	0	1	1	0	1	1	0	1	1	1	
366		.375	0	1	1	1	0	1	1	0	1	1	1	
367		.3875	1	1	1	1	0	1	1	0	1	1	1	
368		170.400	0	0	0	0	1	1	1	0	1	1	1	
369		.4125	1	0	0	0	1	1	1	0	1	1	1	
370		.425	0	1	0	0	1	1	1	0	1	1	1	
371		.4375	1	1	0	0	1	1	1	0	1	1	1	
372		.450	0	0	1	0	1	1	1	0	1	1	1	
373		.4625	1	0	1	0	1	1	1	0	1	1	1	
374		.475	0	1	1	0	1	1	1	0	1	1	1	
375		.4875	1	1	1	0	1	1	1	0	1	1	1	
376		170.500	0	0	0	1	1	1	1	0	1	1	1	
377		.5125	1	0	0	1	1	1	1	0	1	1	1	
378		.525	0	1	0	1	1	1	1	0	1	1	1	
379		.5375	1	1	0	1	1	1	1	0	1	1	1	
380		.550	0	0	1	1	1	1	1	0	1	1	1	
381		.5625	1	0	1	1	1	1	1	0	1	1	1	
382		.575	0	1	1		1	1	1		1	1	1	
HH 383		.5875	1	1	1		1	1	1		1	1	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H. L. N11	NOTE
HH 384		170. 600	0	0	0	0	0	0	0	1	1	1	1	
385		. 6125	1	0	0	0	0	0	0	1	1	1	1	
386		. 625	0	1	0	0	0	0	0	1	1	1	1	
387		. 6375	1	1	0	0	0	0	0	1	1	1	1	
388		. 650	0	0	1	0	0	0	0	1	1	1	1	
389		. 6625	1	0	1	0	0	0	0	1	1	1	1	
390		. 675	0	1	1	0	0	0	0	1	1	1	1	
391		. 6875	1	1	1	0	0	0	0	1	1	1	1	
392		170. 700	0	0	0	1	0	0	0	1	1	1	1	
393		. 7125	1	0	0	1	0	0	0	1	1	1	1	
394		. 725	0	1	0	1	0	0	0	1	1	1	1	
395		. 7375	1	1	0	1	0	0	0	1	1	1	1	
396		. 750	0	0	1	1	0	0	0	1	1	1	1	
397		. 7625	1	0	1	1	0	0	0	1	1	1	1	
398		. 775	0	1	1	1	0	0	0	1	1	1	1	
399		. 7875	1	1	1	1	0	0	0	1	1	1	1	
400		170. 800	0	0	0	0	1	0	0	1	1	1	1	
401		. 8125	1	0	0	0	1	0	0	1	1	1	1	
402		. 825	0	1	0	0	1	0	0	1	1	1	1	
403		. 8375	1	1	0	0	1	0	0	1	1	1	1	
404		. 850	0	0	1	0	1	0	0	1	1	1	1	
405		. 8625	1	0	1	0	1	0	0	1	1	1	1	
406		. 875	0	1	1	0	1	0	0	1	1	1	1	
407		. 8875	1	1	1	0	1	0	0	1	1	1	1	
408		170. 900	0	0	0	1	1	0	0	1	1	1	1	
409		. 9125	1	0	0	1	1	0	0	1	1	1	1	
410		. 925	0	1	0	1	1	0	0	1	1	1	1	
411		. 9375	1	1	0	1	1	0	0	1	1	1	1	
412		. 950	0	0	1	1	1	0	0	1	1	1	1	
413		. 9625	1	0	1	1	1	0	0	1	1	1	1	
414		. 975	0	1	1	1	1	0	0	1	1	1	1	
415		. 9875	1	1	1	1	1	0	0	1	1	1	1	
416		171. 000	0	0	0	0	0	1	0	1	1	1	1	
417		. 0125	1	0	0	0	0	1	0	1	1	1	1	
418		. 025	0	1	0	0	0	1	0	1	1	1	1	
419		. 0375	1	1	0	0	0	1	0	1	1	1	1	
420		. 050	0	0	1	0	0	1	0	1	1	1	1	
421		. 0625	1	0	1	0	0	1	0	1	1	1	1	
422		. 075	0	1	1	0	0	1	0	1	1	1	1	
423		. 0875	1	1	1	0	0	1	0	1	1	1	1	
424		171. 100	0	0	0	1	0	1	0	1	1	1	1	
425		. 1125	1	0	0	1	0	1	0	1	1	1	1	
426		. 125	0	1	0	1	0	1	0	1	1	1	1	
427		. 1375	1	1	0	1	0	1	0	1	1	1	1	
428		. 150	0	0	1	1	0	1	0	1	1	1	1	
429		. 1625	1	0	1	1	0	1	0	1	1	1	1	
430		. 175	0	1	1	1	0	1	0	1	1	1	1	
431		. 1875	1	1	1	1	0	1	0	1	1	1	1	
432		171. 200	0	0	0	0	1	1	0	1	1	1	1	
433		. 2125	1	0	0	0	1	1	0	1	1	1	1	
434		. 225	0	1	0	0	1	1	0	1	1	1	1	
435		. 2375	1	1	0	0	1	1	0	1	1	1	1	
436		. 250	0	0	1	0	1	1	0	1	1	1	1	
437		. 2625	1	0	1	0	1	1	0	1	1	1	1	
438		. 275	0	1	1	0	1	1	0	1	1	1	1	
439		. 2875	1	1	1	0	1	1	0	1	1	1	1	
440		171. 300	0	0	0	1	1	1	0	1	1	1	1	
441		. 3125	1	0	0	1	1	1	0	1	1	1	1	
442		. 325	0	1	0	1	1	1	0	1	1	1	1	
443		. 3375	1	1	0	1	1	1	0	1	1	1	1	
444		. 350	0	0	1	1	1	1	0	1	1	1	1	
445		. 3625	1	0	1	1	1	1	0	1	1	1	1	
446		. 375	0	1	1	1	1	1	0	1	1	1	1	
447		. 3875	1	1	1	1	1	1	0	1	1	1	1	

CHANNEL CODE NO.	STATION	FREQUENCY	N1	N2	N3	N4	N5	N6	N7	N8	N9	N10	H/L N11	NOTE
HH 448		171.400	0	0	0	0	0	0	1	1	1	1	1	
449		.4125	1	0	0	0	0	0	1	1	1	1	1	
450		.425	0	1	0	0	0	0	1	1	1	1	1	
451		.4375	1	1	0	0	0	0	1	1	1	1	1	
452		.450	0	0	1	0	0	0	1	1	1	1	1	
453		.4625	1	0	1	0	0	0	1	1	1	1	1	
454		.475	0	1	1	0	0	0	1	1	1	1	1	
455		.4875	1	1	1	0	0	0	1	1	1	1	1	
456		171.500	0	0	0	1	0	0	1	1	1	1	1	
457		.5125	1	0	0	1	0	0	1	1	1	1	1	
458		.525	0	1	0	1	0	0	1	1	1	1	1	
459		.5375	1	1	0	1	0	0	1	1	1	1	1	
460		.550	0	0	1	1	0	0	1	1	1	1	1	
461		.5625	1	0	1	1	0	0	1	1	1	1	1	
462		.575	0	1	1	1	0	0	1	1	1	1	1	
463		.5875	1	1	1	1	0	0	1	1	1	1	1	
464		171.600	0	0	0	0	1	0	1	1	1	1	1	
465		.6125	1	0	0	0	1	0	1	1	1	1	1	
466		.625	0	1	0	0	1	0	1	1	1	1	1	
467		.6375	1	1	0	0	1	0	1	1	1	1	1	
468		.650	0	0	1	0	1	0	1	1	1	1	1	
469		.6625	1	0	1	0	1	0	1	1	1	1	1	
470		.675	0	1	1	0	1	0	1	1	1	1	1	
471		.6875	1	1	1	0	1	0	1	1	1	1	1	
472		171.700	0	0	0	1	1	0	1	1	1	1	1	
473		.7125	1	0	0	1	1	0	1	1	1	1	1	
474		.725	0	1	0	1	1	0	1	1	1	1	1	
475		.7375	1	1	0	1	1	0	1	1	1	1	1	
476		.750	0	0	1	1	1	0	1	1	1	1	1	
477		.7625	1	0	1	1	1	0	1	1	1	1	1	
478		.775	0	1	1	1	1	0	1	1	1	1	1	
479		.7875	1	1	1	1	1	0	1	1	1	1	1	
480		171.800	0	0	0	0	0	1	1	1	1	1	1	
481		.8125	1	0	0	0	0	1	1	1	1	1	1	
482		.825	0	1	0	0	0	1	1	1	1	1	1	
483		.8375	1	1	0	0	0	1	1	1	1	1	1	
484		.850	0	0	1	0	0	1	1	1	1	1	1	
485		.8625	1	0	1	0	0	1	1	1	1	1	1	
486		.875	0	1	1	0	0	1	1	1	1	1	1	
487		.8875	1	1	1	0	0	1	1	1	1	1	1	
488		171.900	0	0	0	1	0	1	1	1	1	1	1	
489		.9125	1	0	0	1	0	1	1	1	1	1	1	
490		.925	0	1	0	1	0	1	1	1	1	1	1	
491		.9375	1	1	0	1	0	1	1	1	1	1	1	
492		.950	0	0	1	1	0	1	1	1	1	1	1	
493		.9625	1	0	1	1	0	1	1	1	1	1	1	
494		.975	0	1	1	1	0	1	1	1	1	1	1	
495		.9875	1	1	1	1	0	1	1	1	1	1	1	
496		172.000	0	0	0	0	1	1	1	1	1	1	1	
497		.0125	1	0	0	0	1	1	1	1	1	1	1	
498		.025	0	1	0	0	1	1	1	1	1	1	1	
499		.0375	1	1	0	0	1	1	1	1	1	1	1	
500		.050	0	0	1	0	1	1	1	1	1	1	1	
501		.0625	1	0	1	0	1	1	1	1	1	1	1	
502		.075	0	1	1	0	1	1	1	1	1	1	1	
503		.0875	1	1	1	0	1	1	1	1	1	1	1	
504		172.100	0	0	0	1	1	1	1	1	1	1	1	
505		.1125	1	0	0	1	1	1	1	1	1	1	1	
506		.125	0	1	0	1	1	1	1	1	1	1	1	
507		.1375	1	1	0	1	1	1	1	1	1	1	1	
508		.150	0	0	1	1	1	1	1	1	1	1	1	
509		.1625	1	0	1	1	1	1	1	1	1	1	1	
510		.175	0	1	1	1	1	1	1	1	1	1	1	
HH 511		.1875	1	1	1	1	1	1	1	1	1	1	1	